

1.1(2)

11'[1]

11'11'

V

A
B
CA
B
C

aeV

A
B
C-A
-B
-C $[V^2]$ A D E
D B F
E F CA D E
D B F
E F CaeV²A D E
F B G
H I C-A -D -E
-F -B -G
-H -I -CV[V²]A D E
D B F
E F CG J K
J H L
K L IM P Q
P N R
Q R OA D E
D B F
E F CG J K
J H L
K L IM P Q
P N R
Q R O

A	B	C	F	E	D	A	B	C	F	E	D
G	H	I	L	K	J	G	H	I	L	K	J
M	N	O	R	Q	P	M	N	O	R	Q	P

aeV[V²]A D E
D B F
E F CG J K
J H L
K L IM P Q
P N R
Q R O-A -D -E
-D -B -F
-E -F -C-G -J -K
-J -H -L
-K -L -I-M -P -Q
-P -N -R
-Q -R -O

A	B	C	F	E	D	-A	-B	-C	-F	-E	-D
G	H	I	L	K	J	-G	-H	-I	-L	-K	-J
M	N	O	R	Q	P	-M	-N	-O	-R	-Q	-P

[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
A	B	C	D	A	B	C	D			
E	F	G		E	F	G				
H	I	J		H	I	J				

ae[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
-A	-E	-H		-E	-B	-D		-H	-D	-C
-E	-B	-D		-B	-F	-I		-D	-I	-G
-H	-D	-C		-D	-I	-G		-C	-G	-J
A	B	C	D	-A	-B	-C	-D			
E	F	G		-E	-F	-G				
H	I	J		-H	-I	-J				

2.1(1)	$\overline{1}[1]$														
	$\overline{1}$						$\overline{1}\{1\}$								
<hr/>															
V	A						-A								
	B						-B								
	C						-C								
aeV	A						A								
	B						B								
	C						C								
[V ²]	A	D	E				A	D	E						
	D	B	F				D	B	F						
	E	F	C				E	F	C						
aeV ²	A	D	E				-A	-D	-E						
	F	B	G				-F	-B	-G						
	H	I	C				-H	-I	-C						
V[V ²]	A	D	E				G	J	K				M	P	Q
	D	B	F				J	H	L				P	N	R
	E	F	C				K	L	I				Q	R	O
	-A	-D	-E				-G	-J	-K				-M	-P	-Q
	-D	-B	-F				-J	-H	-L				-P	-N	-R
	-E	-F	-C				-K	-L	-I				-Q	-R	-O
	A	B	C	F	E	D				-A	-B	-C	-F	-E	-D
	G	H	I	L	K	J				-G	-H	-I	-L	-K	-J
	M	N	O	R	Q	P				-M	-N	-O	-R	-Q	-P
aeV[V ²]	A	D	E				G	J	K				M	P	Q
	D	B	F				J	H	L				P	N	R
	E	F	C				H	L	I				Q	R	O
	A	D	E				G	J	K				M	P	Q
	D	B	F				J	H	L				P	N	R
	E	F	C				H	L	I				Q	R	O
	A	B	C	F	E	D				A	B	C	F	E	D
	G	H	I	L	K	J				G	H	I	L	K	J
	M	N	O	R	Q	P				M	N	O	R	Q	P

[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
-A	-E	-H		-E	-B	-D		-H	-D	-C
-E	-B	-D		-B	-F	-I		-D	-I	-G
-H	-D	-C		-D	-I	-G		-C	-G	-J
A	B	C	D	-A	-B	-C	-D			
E	F	G		-E	-F	-G				
H	I	J		-H	-I	-J				

ae[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
A	B	C	D	A	B	C	D			
E	F	G		E	F	G				
H	I	J		H	I	J				

2.4(4)	$\overline{1}1'[\overline{1}']$											
	$\overline{1}'\underline{1}'$						$\overline{1}(1)\underline{1}'$					
<hr/>												
V	0						0					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	0						0					
[V ²]	A	D	E				A	D	E			
	D	B	F				D	B	F			
	E	F	C				E	F	C			
aeV ²	A	D	E				-A	-D	-E			
	F	B	G				-F	-B	-G			
	H	I	C				-H	-I	-C			
V[V ²]	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
aeV[V ²]	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

2.5(5)	$\overline{1}'[1]$														
	$\underline{\overline{1}}'$						$\overline{1}(1)\{1\}$								
<hr/>															
V	A						-A								
	B						-B								
	C						-C								
aeV	A						-A								
	B						-B								
	C						-C								
[V ²]	A	D	E				A	D	E						
	D	B	F				D	B	F						
	E	F	C				E	F	C						
aeV ²	A	D	E				A	D	E						
	F	B	G				F	B	G						
	H	I	C				H	I	C						
V[V ²]	A	D	E				G	J	K				M	P	Q
	D	B	F				J	H	L				P	N	R
	E	F	C				K	L	I				Q	R	O
	-A	-D	-E				-G	-J	-K				-M	-P	-Q
	-D	-B	-F				-J	-H	-L				-P	-N	-R
	-E	-F	-C				-K	-L	-I				-Q	-R	-O
	A	B	C	F	E	D				-A	-B	-C	-F	-E	-D
	G	H	I	L	K	J				-G	-H	-I	-L	-K	-J
	M	N	O	R	Q	P				-M	-N	-O	-R	-Q	-P
aeV[V ²]	A	D	E				G	J	K				M	P	Q
	D	B	F				J	H	L				P	N	R
	E	F	C				K	L	I				Q	R	O
	-A	-D	-E				-G	-J	-K				-M	-P	-Q
	-D	-B	-F				-J	-H	-L				-P	-N	-R
	-E	-F	-C				-K	-L	-I				-Q	-R	-O
	A	B	C	F	E	D				-A	-B	-C	-F	-E	-D
	G	H	I	L	K	J				-G	-H	-I	-L	-K	-J
	M	N	O	R	Q	P				-M	-N	-O	-R	-Q	-P

[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
-A	-E	-H		-E	-B	-D		-H	-D	-C
-E	-B	-D		-B	-F	-I		-D	-I	-G
-H	-D	-C		-D	-I	-G		-C	-G	-J
A	B	C	D	-A	-B	-C	-D			
E	F	G		-E	-F	-G				
H	I	J		-H	-I	-J				

ae[V³]

A	E	H		E	B	D		H	D	C
E	B	D		B	F	I		D	I	G
H	D	C		D	I	G		C	G	J
-A	-E	-H		-E	-B	-D		-H	-D	-C
-E	-B	-D		-B	-F	-I		-D	-I	-G
-H	-D	-C		-D	-I	-G		-C	-G	-J
A	B	C	D	-A	-B	-C	-D			
E	F	G		-E	-F	-G				
H	I	J		-H	-I	-J				

3.2(2)

$2_z 1' [2_z]$

$2_z \underline{1}'$

$2_z \underline{1}'$

V	0 0 A					0 0 A					
aeV	0 0 A					0 0 -A					
$[V^2]$	A D 0 D B 0 0 0 C					A D 0 D B 0 0 0 C					
aeV ²	A D 0 E B 0 0 0 C					-A -D 0 -E -B 0 0 0 -C					
V[V ²]	0 0 A 0 0 B A B 0					0 0 C 0 0 D C D 0			E H 0 H F 0 0 0 G		
	0 0 A 0 0 B A B 0					0 0 C 0 0 D C D 0			E H 0 H F 0 0 0 G		
	0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H					0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H					
aeV[V ²]	0 0 A 0 0 B A B 0					0 0 C 0 0 D C D 0			E H 0 H F 0 0 0 G		
	0 0 -A 0 0 -B -A -B 0					0 0 -C 0 0 -D -C -D 0			-E -H 0 -H -F 0 0 0 -G		
	0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H					0 0 0 -B -A 0 0 0 0 -D -C 0 -E -F -G 0 0 -H					

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
B	D	C			B	D	C			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	D	C			-B	-D	-C			

3.4(4)

$2_z 1' [2_z']$

$2_z' \underline{1}'$

$2_z(1) \underline{1}'$

V	0 0 A					0 0 A					
aeV	A B 0					-A -B 0					
$[V^2]$	A D 0 D B 0 0 0 C					A D 0 D B 0 0 0 C					
aeV ²	0 0 A 0 0 B C D 0					0 0 -A 0 0 -B -C -D 0					
V[V ²]	0 0 A 0 0 B A B 0					0 0 C 0 0 D C D 0			E H 0 H F 0 0 0 G		
	0 0 A 0 0 B A B 0					0 0 C 0 0 D C D 0			E H 0 H F 0 0 0 G		
	0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H					0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H					
aeV[V ²]	A D 0 D B 0 0 0 C					E H 0 H F 0 0 0 G			0 0 I 0 0 J I J 0		
	-A -D 0 -D -B 0 0 0 -C					-E -H 0 -H -F 0 0 0 -G			0 0 -I 0 0 -J -I -J 0		
	A B C 0 0 D E F G 0 0 H 0 0 0 J I 0					-A -B -C 0 0 -D -E -F -G 0 0 -H 0 0 0 -J -I 0					

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
B	D	C			B	D	C			

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0		-A	-B	-C		0	
D	E	F			-D	-E	-F			
0	0	0			0	0	0			

4.2(2)

$m_z 1' [m_z]$

$m_z \underline{1}'$

$m_z \underline{1}'$

V	A B 0		A B 0
aeV	0 0 A		0 0 -A
$[V^2]$	A D 0 D B 0 0 0 C		A D 0 D B 0 0 0 C
aeV ²	0 0 A 0 0 B C D 0		0 0 -A 0 0 -B -A -B 0
V[V ²]	A D 0 D B 0 0 0 C	E H 0 H F 0 0 0 G	0 0 I 0 0 J I J 0
	A D 0 D B 0 0 0 C	E H 0 H F 0 0 0 G	0 0 I 0 0 J I J 0
	A B C 0 0 D E F G 0 0 H 0 0 0 J I 0		A B C 0 0 D E F G 0 0 H 0 0 0 J I 0
aeV[V ²]	0 0 A 0 0 B A B 0	0 0 C 0 0 D C D 0	E H 0 H F 0 0 0 G
	0 0 -A 0 0 -B -A -B 0	0 0 -C 0 0 -D -C -D 0	-E -H 0 -H -F 0 0 0 -G
	0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H		0 0 0 -B -A 0 0 0 0 -D -C 0 -E -F -G 0 0 -H

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	B	C	0	A	B	C	0			
D	E	F		D	E	F				
0	0	0		0	0	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	D	C		-B	-D	-C				

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0

A	B	C	0		A	B	C	0
D	E	F			D	E	F	
0	0	0			0	0	0	

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0

-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0

A	B	C	0		-A	-B	-C	0
D	E	F			-D	-E	-F	
0	0	0			0	0	0	

5.1(1)

$2_z/m_z[2_z]$

$2_z/\underline{m}_z$

$2_z/m_z\{2_z\}$

<hr/>														
V	0									0				
	0									0				
	A									-A				
aeV	0									0				
	0									0				
	A									A				
[V ²]	A	D	0							A	D	0		
	D	B	0							D	B	0		
	0	0	C							0	0	C		
aeV ²	A	D	0							-A	-D	0		
	E	B	0							-E	-B	0		
	0	0	C							0	0	-C		
V[V ²]	0	0	A							0	0	C		
	0	0	B							0	0	D		
	A	B	0							C	D	0		
													E	H
													F	0
													0	G
	0	0	-A							0	0	-C		
	0	0	-B							0	0	-D		
	-A	-B	0							-C	-D	0		
													-E	-H
													F	0
													0	-G
aeV[V ²]	0	0	0	B	A	0				0	0	0	-B	-A
	0	0	0	D	C	0				0	0	0	-D	-C
	E	F	G	0	0	H				-E	-F	-G	0	0
													0	-H
	0	0	A							0	0	C		
	0	0	B							0	0	D		
	A	B	0							C	D	0		
													E	H
													F	0
													0	G
	0	0	A							0	0	C		
	0	0	B							0	0	D		
	A	B	0							C	D	0		
aeV[V ²]	0	0	0	B	A	0				0	0	0	B	A
	0	0	0	D	C	0				0	0	0	D	C
	E	F	G	0	0	H				E	F	G	0	0
													0	H
	0	0	A							0	0	C		
	0	0	B							0	0	D		
	A	B	0							C	D	0		
													E	H
													F	0
													0	G
	0	0	A							0	0	C		
	0	0	B							0	0	D		
	A	B	0							C	D	0		

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	D	C			-B	-D	-C			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
B	D	C			B	D	C			

5.2(1)

 $2_z/m_z[m_z]$ $\underline{2}_z/m_z$ $2_z/m_z\{m_z\}$

V	A					-A								
	B					-B								
	0					0								
aeV	0					0								
	0					0								
	A					A								
[V ²]	A	D	0			A	D	0						
	D	B	0			D	B	0						
	0	0	C			0	0	C						
aeV ²	0	0	A			0	0	-A						
	0	0	B			0	0	-B						
	C	D	0			-C	-D	0						
V[V ²]	A	D	0			E	H	0			0	0	I	
	D	B	0			H	F	0			0	0	J	
	0	0	C			0	0	G			I	J	0	
	-A	-D	0			-E	-H	0			0	0	-I	
	-D	-B	0			-H	-F	0			0	0	-J	
	0	0	-C			0	0	-G			-I	-J	0	
	A	B	C	0	0	D			-A	-B	-C	0	0	-D
	E	F	G	0	0	H			-E	-F	-G	0	0	-H
	0	0	0	J	I	0			0	0	0	-J	-I	0
aeV[V ²]	0	0	A			0	0	C			E	H	0	
	0	0	B			0	0	D			H	F	0	
	A	B	0			C	D	0			0	0	G	
	0	0	A			0	0	C			E	H	0	
	0	0	B			0	0	D			H	F	0	
	A	B	0			C	D	0			0	0	G	
	0	0	0	B	A	0			0	0	0	B	A	0
	0	0	0	D	C	0			0	0	0	D	C	0
	E	F	G	0	0	H			E	F	G	0	0	H

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	D	C		B	D	C				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$2_z/m_z \perp [2_z'/m_z]$$
$$2_z/m_z(m_z) \underline{1}$$

V	0 0 0		0 0 0
aeV	0 0 0		0 0 0
[V ²]	A D 0 D B 0 0 0 C		A D 0 D B 0 0 0 C
aeV ²	0 0 A 0 0 B C D 0		0 0 -A 0 0 -B -A -B 0
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

	$\underline{2}_z\text{'}/m_z$	$2_z/m_z(m_z)\{m_z\}$
V	A B 0	-A -B 0
aeV	0 0 A	0 0 -A
[V ²]	A D 0 D B 0 0 0 C	A D 0 D B 0 0 0 C
aeV ²	0 0 A 0 0 B C D 0	0 0 A 0 0 B C D 0
V[V ²]	A D 0 D B 0 0 0 C -A -D 0 -D -B 0 0 0 -C A B C 0 0 D E F G 0 0 H 0 0 0 J I 0	E H 0 H F 0 0 0 G -E -H 0 -H -F 0 0 0 -G -A -B -C 0 0 -D -E -F -G 0 0 -H 0 0 0 -J -I 0
aeV[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H	0 0 C 0 0 D C D 0 0 0 -C 0 0 -D -C -D 0 0 0 0 -B -A 0 0 0 0 -D -C 0 -E -F -G 0 0 -H

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	D	C		-B	-D	-C				

$$5.12(6) \quad 2_z' / m_z [2_z']$$

$$2_z' / \underline{m}_z \quad 2_z / m_z(m_z) \{2_z(1)\}$$

V	0 0 A	0 0 -A
aeV	A B 0	-A -B 0
[V ²]	A D 0 D B 0 0 0 C	A D 0 D B 0 0 0 C
aeV ²	0 0 A 0 0 B C D 0	0 0 A 0 0 B C D 0
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H	0 0 C 0 0 D C D 0 0 0 -C 0 0 -D -C -D 0 0 0 0 -B -A 0 0 0 0 -D -C 0 -E -F -G 0 0 -H
aeV[V ²]	A D 0 D B 0 0 0 C -A -D 0 -D -B 0 0 0 -C A B C 0 0 D E F G 0 0 H 0 0 0 J I 0	E H 0 H F 0 0 0 G -E -H 0 -H -F 0 0 0 -G 0 0 I 0 0 J I J 0 0 0 -I 0 0 -J -I -J 0 -A -B -C 0 0 -D -E -F -G 0 0 -H 0 0 0 -J -I 0

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	D	C		-B	-D	-C				

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	D	C			-B	-D	-C			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	D	C			-B	-D	-C			

$$5.16(6) \quad 2_z/m_z' [m_z']$$

$$\frac{2_z}{m_z} \cdot \frac{2_z}{m_z} \{m_z(1)\}$$

V	A					-A								
	B					-B								
	0					0								
aeV	A					-A								
	B					-B								
	0					0								
[V ²]	A	D	0			A	D	0						
	D	B	0			D	B	0						
	0	0	C			0	0	C						
aeV ²	A	D	0			A	D	0						
	E	B	0			E	B	0						
	0	0	C			0	0	C						
V[V ²]	A	D	0			E	H	0			0	0	I	
	D	B	0			H	F	0			0	0	J	
	0	0	C			0	0	G			I	J	0	
	-A	-D	0			-E	-H	0			0	0	-I	
	-D	-B	0			-H	-F	0			0	0	-J	
	0	0	-C			0	0	-G			-I	-J	0	
	A	B	C	0	0	D			-A	-B	-C	0	0	-D
	E	F	G	0	0	H			-E	-F	-G	0	0	-H
	0	0	0	J	I	0			0	0	0	-J	-I	0
aeV[V ²]	A	D	0			E	H	0			0	0	I	
	D	B	0			H	F	0			0	0	J	
	0	0	C			0	0	G			I	J	0	
	-A	-D	0			-E	-H	0			0	0	-I	
	-D	-B	0			-H	-F	0			0	0	-J	
	0	0	-C			0	0	-G			-I	-J	0	
	A	B	C	0	0	D			-A	-B	-C	0	0	-D
	E	F	G	0	0	H			-E	-F	-G	0	0	-H
	0	0	0	J	I	0			0	0	0	-J	-I	0

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

5.18(6)

$2_z' / m_z' [2_z']$

$2_z' / \underline{m_z}'$

$2_z / m_z(\overline{1}) \{2_z(1)\}$

V	0 0 A	0 0 -A
aeV	A B 0	A B 0
$[V^2]$	A D 0 D B 0 0 0 C	A D 0 D B 0 0 0 C
aeV ²	0 0 A 0 0 B C D 0	0 0 -A 0 0 -B -A -B 0
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 D C 0 E F G 0 0 H	0 0 C 0 0 D C D 0 0 0 -C 0 0 -D -C -D 0 0 0 0 -B -A 0 0 0 0 -D -C 0 -E -F -G 0 0 -H
aeV[V ²]	A D 0 D B 0 0 0 C A D 0 D B 0 0 0 C A B C 0 0 D E F G 0 0 H 0 0 0 J I 0	E H 0 H F 0 0 0 G E H 0 H F 0 0 0 G 0 0 I 0 0 J I J 0 A B C 0 0 D E F G 0 0 H 0 0 0 J I 0

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	D		A	D	0
B	A	0		A	D	0		0	0	C
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	-D		-A	-D	0
-B	-A	0		-A	-D	0		0	0	-C
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	D	C		-B	-D	-C				

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	B	C	0	A	B	C	0			
D	E	F		D	E	F				
0	0	0		0	0	0				

	$\underline{2}_z' / m_z'$	$2_z / m_z(\overline{1}) \{ m_z(1) \}$
V	A B 0	-A -B 0
aeV	A B 0	A B 0
$[V^2]$	A D 0 D B 0 0 0 C	A D 0 D B 0 0 0 C
aeV ²	A D 0 E B 0 0 0 C	-A -D 0 -E -B 0 0 0 -C
V[V ²]	A D 0 D B 0 0 0 C -A -D 0 -D -B 0 0 0 -C A B C 0 0 D E F G 0 0 H 0 0 0 J I 0	E H 0 H F 0 0 0 G -E -H 0 -H -F 0 0 0 -G -A -B -C 0 0 -D -E -F -G 0 0 -H 0 0 0 -J -I 0
aeV[V ²]	A D 0 D B 0 0 0 C A D 0 D B 0 0 0 C A B C 0 0 D E F G 0 0 H 0 0 0 J I 0	E H 0 H F 0 0 0 G E H 0 H F 0 0 0 G A B C 0 0 D E F G 0 0 H 0 0 0 J I 0

[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
-A	-D	0		-D	-B	0		0	0	-C
-D	-B	0		-B	-E	0		0	0	-F
0	0	-C		0	0	-F		-C	-F	0
A	B	C	0	-A	-B	-C	0			
D	E	F		-D	-E	-F				
0	0	0		0	0	0				

ae[V³]

A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	D	0		D	B	0		0	0	C
D	B	0		B	E	0		0	0	F
0	0	C		0	0	F		C	F	0
A	B	C	0	A	B	C	0			
D	E	F		D	E	F				
0	0	0		0	0	0				

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			-A	-B	-C			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			A	B	C			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

7.6(4)

$m_x m_y 2_z 1' [m_x' m_y 2_z']$

$m_x' m_y 2_z' \underline{1}'$

$m_x m_y 2_z (m_y) \underline{1}'$

V	0 0 A	0 0 A
aeV	0 A 0	0 -A 0
$[V^2]$	A 0 0 0 B 0 0 0 C	A 0 0 0 B 0 0 0 C
aeV ²	0 0 0 0 0 A 0 B 0	0 0 0 0 0 -A 0 -B 0
V $[V^2]$	0 0 A 0 0 0 A 0 0 0 0 A 0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 B 0 B 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0
aeV $[V^2]$	0 B 0 B 0 0 0 0 0 0 -B 0 -B 0 0 0 0 0 0 0 0 0 0 B D E C 0 0 0 0 0 0 A 0 0	D 0 0 0 E 0 0 0 C -D 0 0 0 -E 0 0 0 -C 0 0 0 -D -E -C 0 0 0 0 0 0 -A 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			A	B	C			

ae[V³]

0	B	0		B	0	0		0	0	0
B	0	0		0	C	0		0	0	A
0	0	0		0	0	A		0	A	0
0	-B	0		-B	0	0		0	0	0
-B	0	0		0	-C	0		0	0	-A
0	0	0		0	0	-A		0	-A	0
0	0	0	0		0	0	0	0		
B	C	A			-B	-C	-A			
0	0	0			0	0	0			

7.7(4)

$m_x m_y 2_z 1' [m_x' m_y' 2_z]$

$m_x' m_y' 2_z \underline{1}'$

$m_x m_y 2_z (2_z) \underline{1}'$

V	0 0 A	0 0 A
aeV	0 0 A	0 0 -A
$[V^2]$	A 0 0 0 B 0 0 0 C	A 0 0 0 B 0 0 0 C
aeV ²	A 0 0 0 B 0 0 0 C	-A 0 0 0 -B 0 0 0 -C
V[V ²]	0 0 A 0 0 0 A 0 0 0 0 A 0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 B 0 B 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0
aeV[V ²]	0 0 A 0 0 0 A 0 0 0 0 -A 0 0 0 -A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 -B 0 -B 0 0 0 0 0 -A 0 0 0 0 -B 0 0 -C -D -E 0 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			A	B	C			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			-A	-B	-C			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		-A	-B	-C				

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

8.8(4) $m_x m_y m_z \underline{1}' [m_x' m_y m_z]$

	$m_x' m_y m_z \underline{1}'$			$m_x m_y m_z (m_y m_z 2_x) \underline{1}'$											
<hr/>															
V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	B	0				0	B	0						
	0	0	C				0	0	C						
aeV ²	0	0	0				0	0	0						
	0	0	A				0	0	-A						
	0	B	0				0	-B	0						
V[V ²]	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

	$m_x 'm_y 'm_z ' \underline{1} '$	$m_x m_y m_z (2_x 2_y 2_z) \underline{1} '$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
[V ²]	A 0 0 0 B 0 0 0 C	A 0 0 0 B 0 0 0 C
aeV ²	A 0 0 0 B 0 0 0 C	-A 0 0 0 -B 0 0 0 -C
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

[V³]

C	0	0		0	A	0		0	0	B
0	A	0		A	0	0		0	0	0
0	0	B		0	0	0		B	0	0
-C	0	0		0	-A	0		0	0	-B
0	-A	0		-A	0	0		0	0	0
0	0	-B		0	0	0		-B	0	0
C	A	B	0	-C	-A	-B	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
0	0	0		0	0	0				

8.12(6)

$m_x' m_y m_z [m_x' m_y 2_z']$

$m_x' m_y m_z$

$m_x m_y m_z (m_y m_z 2_x) \{m_x m_y 2_z (m_y)\}$

V	0 0 A	0 0 -A
aeV	0 A 0	0 -A 0
$[V^2]$	A 0 0 0 B 0 0 0 C	A 0 0 0 B 0 0 0 C
aeV ²	0 0 0 0 0 A 0 B 0	0 0 0 0 0 A 0 B 0
V[V ²]	0 0 A 0 0 0 A 0 0 0 0 -A 0 0 0 -A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 -B 0 -B 0 0 0 0 0 -A 0 0 0 0 -B 0 0 -C -D -E 0 0 0
aeV[V ²]	0 B 0 B 0 0 0 0 0 0 -B 0 -B 0 0 0 0 0 0 0 0 0 0 B D E C 0 0 0 0 0 0 A 0 0	D 0 0 0 E 0 0 0 C -D 0 0 0 -E 0 0 0 -C 0 0 0 0 0 -B -D -E -C 0 0 0 0 0 0 -A 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		-A	-B	-C				

ae[V³]

0	B	0		B	0	0		0	0	0
B	0	0		0	C	0		0	0	A
0	0	0		0	0	A		0	A	0
0	-B	0		-B	0	0		0	0	0
-B	0	0		0	-C	0		0	0	-A
0	0	0		0	0	-A		0	-A	0
0	0	0	0	0	0	0	0			
B	C	A		B	C	A				
0	0	0		0	0	0				

$$8.15(6) \quad m_x' m_y m_z [2_x 2_y' 2_z']$$

$$\underline{m}_x \cdot \underline{m}_y \underline{m}_z$$

$$m_x m_y m_z (m_y m_z 2_x) \{2_x 2_y 2_z (2_x)\}$$

V	0 0 0		0 0 0
aeV	A 0 0		-A 0 0
[V ²]	A 0 0 0 B 0 0 0 C		A 0 0 0 B 0 0 0 C
aeV ²	0 0 0 0 0 A 0 B 0		0 0 0 0 0 A 0 B 0
V[V ²]	0 0 0 0 0 A 0 A 0 0 0 0 0 0 -A 0 -A 0 0 0 0 A 0 0 0 0 0 0 B 0 0 0 0 0 0 C		0 0 B 0 0 0 B 0 0 0 0 -B 0 0 0 -B 0 0 0 0 0 -A 0 0 0 0 0 0 -B 0 0 0 0 0 0 -C
aeV[V ²]	E 0 0 0 C 0 0 0 D -E 0 0 0 -C 0 0 0 -D E C D 0 0 0 0 0 0 0 0 A 0 0 0 0 B 0		0 A 0 A 0 0 0 0 0 0 -A 0 -A 0 0 0 0 0 -E -C -D 0 0 0 0 0 0 0 0 -A 0 0 0 0 -B 0

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

C	0	0		0	A	0		0	0	B
0	A	0		A	0	0		0	0	0
0	0	B		0	0	0		B	0	0
-C	0	0		0	-A	0		0	0	-B
0	-A	0		-A	0	0		0	0	0
0	0	-B		0	0	0		-B	0	0
C	A	B	0		-C	-A	-B	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

8.17(6)

$m_x' m_y' m_z [m_x' m_y' 2_z]$

$m_x' m_y' \underline{m_z}$

$m_x m_y m_z (2_z / m_z) \{m_x m_y 2_z (2_z)\}$

V	0 0 A	0 0 -A
aeV	0 0 A	0 0 A
$[V^2]$	A 0 0 0 C 0 0 0 D	A 0 0 0 B 0 0 0 C
aeV ²	A 0 0 0 B 0 0 0 C	-A 0 0 0 -B 0 0 0 -C
V[V ²]	0 0 A 0 0 0 A 0 0 0 0 -A 0 0 0 -A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 -B 0 -B 0 0 0 0 0 -A 0 0 0 0 -B 0 0 -C -D -E 0 0 0
aeV[V ²]	0 0 A 0 0 0 A 0 0 0 0 A 0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0	0 0 0 0 0 B 0 B 0 0 0 0 0 0 B 0 B 0 0 0 0 0 A 0 0 0 0 B 0 0 C D E 0 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		-A	-B	-C				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		A	B	C				

$$8.18(6) \quad m_x' m_y' m_z [m_y' m_z 2_x']$$

$$\underline{m}_x \cdot m_y \cdot m_z$$

$$m_x m_y m_z (2_z / m_z) \{ m_y m_z 2_x (m_z) \}$$

V	A						-A					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	A						A					
[V ²]	A	0	0				A	0	0			
	0	B	0				0	B	0			
	0	0	C				0	0	C			
aeV ²	0	0	A				0	0	-A			
	0	0	0				0	0	0			
	B	0	0				-B	0	0			
V[V ²]	E	0	0				0	A	0			
	0	C	0				A	0	0			
	0	0	D				0	0	0			
	0	0	0				0	0	0			
	-E	0	0				0	-A	0			
	0	-C	0				-A	0	0			
	0	0	-D				0	0	0			
	0	0	0				0	0	0			
	-B	0	0				-B	0	0			
	E	C	D	0	0	0	-E	-C	-D	0	0	0
	0	0	0	0	0	A	0	0	0	0	0	-A
	0	0	0	0	B	0	0	0	0	0	-B	0
aeV[V ²]	0	0	A				0	0	0			
	0	0	0				0	0	B			
	A	0	0				0	B	0			
	0	0	A				0	0	0			
	0	0	0				0	0	B			
	A	0	0				0	B	0			
	0	0	0				0	0	0			
	0	0	0				0	0	B			
	A	0	0				0	B	0			
	0	0	0	0	A	0	0	0	0	0	A	0
	0	0	0	B	0	0	0	0	0	B	0	0
	C	D	E	0	0	0	C	D	E	0	0	0

[V³]

C	0	0		0	A	0		0	0	B
0	A	0		A	0	0		0	0	0
0	0	B		0	0	0		B	0	0
-C	0	0		0	-A	0		0	0	-B
0	-A	0		-A	0	0		0	0	0
0	0	-B		0	0	0		-B	0	0
C	A	B	0	-C	-A	-B	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		A	B	C				

$$m_x \cdot m_y \cdot m_z [2_x \cdot 2_y \cdot 2_z]$$
$$m_x m_y m_z (2_z / m_z) \{ 2_x 2_y 2_z (2_z) \}$$

V	0						0					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	A						A					
[V ²]	A	0	0				A	0	0			
	0	B	0				0	B	0			
	0	0	C				0	0	C			
aeV ²	0	A	0				0	-A	0			
	B	0	0				-B	0	0			
	0	0	0				0	0	0			
V[V ²]	0	0	0				0	0	B			
	0	0	A				0	0	0			
	0	A	0				B	0	0			
	0	0	0				0	0	-B			
	0	0	-A				0	0	0			
	0	-A	0				-B	0	0			
	0	0	0	A	0	0	0	0	0	-A	0	0
	0	0	0	0	B	0	0	0	0	0	-B	0
	0	0	0	0	0	C	0	0	0	0	0	-C
aeV[V ²]	0	0	A				0	0	0			
	0	0	0				0	0	B			
	A	0	0				0	B	0			
	0	0	A				0	0	0			
	0	0	0				0	0	B			
	A	0	0				0	B	0			
	0	0	0	0	A	0	0	0	0	0	A	0
	0	0	0	B	0	0	0	0	0	0	B	0
	C	D	E	0	0	0	C	D	E	0	0	0

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	B	C			A	B	C			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

8.22(6)

$m_x' m_y' m_z' [m_x' m_y' 2_z]$

$m_x' m_y' \underline{m_z'}$

$m_x m_y m_z (2_x 2_y 2_z) \{m_x m_y 2_z (2_z)\}$

V	0	0	
	0	0	
	A	-A	
aeV	0	0	
	0	0	
	A	-A	
[V ²]	A 0 0	A 0 0	
	0 B 0	0 B 0	
	0 0 C	0 0 C	
aeV ²	A 0 0	A 0 0	
	0 B 0	0 B 0	
	0 0 C	0 0 C	
V[V ²]	0 0 A	0 0 0	C 0 0
	0 0 0	0 0 B	0 D 0
	A 0 0	0 B 0	0 0 E
	0 0 -A	0 0 -B	-C 0 0
	0 0 0	0 0 0	0 -D 0
	-A 0 0	0 -B 0	0 0 -E
	0 0 0 0 A 0	0 0 0 0 -A 0	
	0 0 0 B 0 0	0 0 0 -B 0 0	
	C D E 0 0 0	-C -D -E 0 0 0	
aeV[V ²]	0 0 A	0 0 0	C 0 0
	0 0 0	0 0 B	0 D 0
	A 0 0	0 B 0	0 0 E
	0 0 -A	0 0 -B	-C 0 0
	0 0 0	0 0 0	0 -D 0
	-A 0 0	0 -B 0	0 0 -E
	0 0 0 0 A 0	0 0 0 0 -A 0	
	0 0 0 B 0 0	0 0 0 -B 0 0	
	C D E 0 0 0	-C -D -E 0 0 0	

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		-A	-B	-C				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	B		0	B	0
A	0	0		0	B	0		0	0	C
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-B		0	-B	0
-A	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	B	C		-A	-B	-C				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

9.4(4)

$4_z 1' [4_z']$

$4_z' \underline{1}'$

$4_z(2_z) \underline{1}'$

V	0 0 A				0 0 A
aeV	0 0 0				0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 B				A 0 0 0 A 0 0 0 B
aeV ²	A B 0 B -A 0 0 0 0				-A -B 0 -B A 0 0 0 0
V[V ²]	0 0 A 0 0 B A B 0	0 0 -B 0 0 A -B A 0	C 0 0 0 C 0 0 0 D		
	0 0 A 0 0 B A B 0	0 0 -B 0 0 A -B A 0	C 0 0 0 C 0 0 0 D		
	0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0		0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0		
aeV[V ²]	0 0 A 0 0 B A B 0	0 0 B 0 0 -A B -A 0	C D 0 D -C 0 0 0 0		
	0 0 -A 0 0 -B -A -B 0	0 0 -B 0 0 A -B A 0	-C -D 0 -D C 0 0 0 0		
	0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D		0 0 0 -B -A 0 0 0 0 A -B 0 -C C 0 0 0 -D		

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	-B	0			-B	B	0			

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		B	-B	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
B	-B	0			B	-B	0			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	-B	0			-B	B	0			

11.2(1)

$4_z/m_z[4_z]$

$4_z/\underline{m}_z$

$4_z/m_z\{4_z\}$

V	0 0 A	0 0 -A
aeV	0 0 A	0 0 A
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A C 0 -C A 0 0 0 B	-A -C 0 C -A 0 0 0 B
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 -B 0 0 A -B A 0 0 0 B 0 0 -A B -A 0 0 0 0 -B -A 0 0 0 0 -A B 0 -C -C -D 0 0 0
aeV[V ²]	0 0 A 0 0 B A B 0 0 0 A 0 0 B A B 0 0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 -B 0 0 A -B A 0 0 0 -B 0 0 A -B A 0 0 0 0 -B -A 0 0 0 0 -A B 0 C C D 0 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

11.10(6)

$4_z' / m_z [4_z']$

$4_z' / \underline{m_z}$

$4_z / m_z (2_z / m_z) \{4_z (2_z)\}$

V	0 0 A	0 0 -A	
aeV	0 0 0	0 0 0	
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B	
aeV ²	A B 0 B -A 0 0 0 0	-A -B 0 -B A 0 0 0 0	
V[V ²]	0 0 A 0 0 B A B 0	0 0 -B 0 0 A -B A 0	C 0 0 0 C 0 0 0 D
	0 0 -A 0 0 -B -A -B 0	0 0 B 0 0 -A B -A 0	-C 0 0 0 -C 0 0 0 -D
	0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 0 -B -A 0 0 0 0 -A B 0 -C -C -D 0 0 0	
aeV[V ²]	0 0 A 0 0 B A B 0	0 0 B 0 0 -A B -A 0	C D 0 D -C 0 0 0 0
	0 0 A 0 0 B A B 0	0 0 B 0 0 -A B -A 0	C D 0 D -C 0 0 0 0
	0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		B	-B	0				

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		B	-B	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

11.13(6) $4_z/m_z' [\overline{4}_z']$

$\underline{4}_z/\underline{m}_z'$

$4_z/m_z(4_z)\{\overline{4}_z(2_z)\}$

V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A C 0 -C A 0 0 0 B	A C 0 -C A 0 0 0 B
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	0 0 B 0 0 -A B -A 0 0 0 -B 0 0 A -B A 0 0 0 0 -B -A 0 0 0 0 A -B 0 -C C 0 0 0 -D
aeV[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	0 0 B 0 0 -A B -A 0 0 0 -B 0 0 A -B A 0 0 0 0 -B -A 0 0 0 0 A -B 0 -C C 0 0 0 -D

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	-B	0			-B	B	0			

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
B	-B	0			-B	B	0			

$$11.15(5) \quad \underline{4}_z' / \underline{m}_z' [\overline{4}_z]$$

$$\underline{4}_z' / \underline{m}_z'$$

$$\underline{4}_z / \underline{m}_z (\overline{4}_z) \{ \overline{4}_z \}$$

V	0 0 0	0 0 0
aeV	0 0 A	0 0 -A
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A B 0 B -A 0 0 0 0	A B 0 B -A 0 0 0 0
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	0 0 B 0 0 -A B -A 0 0 0 -B 0 0 A -B A 0 0 0 0 -B -A 0 0 0 0 A -B 0 -C C 0 0 0 -D
aeV[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 A -B 0	0 0 -B 0 0 A -B A 0 0 0 B 0 0 -A B -A 0 C 0 0 0 C 0 0 0 D -C 0 0 0 -C 0 0 0 -D

$$\begin{array}{cccccc} C & C & D & 0 & 0 & 0 \end{array} \qquad \begin{array}{cccccc} -C & -C & -D & 0 & 0 & 0 \end{array}$$

$[V^3]$

$$\begin{array}{ccc} 0 & 0 & B \\ 0 & 0 & A \\ B & A & 0 \end{array} \qquad \begin{array}{ccc} 0 & 0 & A \\ 0 & 0 & -B \\ A & -B & 0 \end{array} \qquad \begin{array}{ccc} B & A & 0 \\ A & -B & 0 \\ 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc} 0 & 0 & -B \\ 0 & 0 & -A \\ -B & -A & 0 \end{array} \qquad \begin{array}{ccc} 0 & 0 & -A \\ 0 & 0 & B \\ -A & B & 0 \end{array} \qquad \begin{array}{ccc} -B & -A & 0 \\ -A & B & 0 \\ 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc} 0 & 0 & 0 & A \\ 0 & 0 & 0 & \\ B & -B & 0 & \end{array} \qquad \begin{array}{ccc} 0 & 0 & 0 & -A \\ 0 & 0 & 0 & \\ -B & B & 0 & \end{array}$$

$ae[V^3]$

$$\begin{array}{ccc} 0 & 0 & A \\ 0 & 0 & 0 \\ A & 0 & 0 \end{array} \qquad \begin{array}{ccc} 0 & 0 & 0 \\ 0 & 0 & A \\ 0 & A & 0 \end{array} \qquad \begin{array}{ccc} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & B \end{array}$$

$$\begin{array}{ccc} 0 & 0 & -A \\ 0 & 0 & 0 \\ -A & 0 & 0 \end{array} \qquad \begin{array}{ccc} 0 & 0 & 0 \\ 0 & 0 & -A \\ 0 & -A & 0 \end{array} \qquad \begin{array}{ccc} -A & 0 & 0 \\ 0 & -A & 0 \\ 0 & 0 & -B \end{array}$$

$$\begin{array}{ccc} 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & \\ A & A & B & \end{array} \qquad \begin{array}{ccc} 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & \\ -A & -A & -B & \end{array}$$

	$4_z \text{ ' / } \underline{m_z} \text{ '}$	$4_z / m_z (\overline{4_z}) \{ 4_z (2_z) \}$
V	0 0 A	0 0 -A
aeV	0 0 0	0 0 0
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A B 0 B -A 0 0 0 0	A B 0 B -A 0 0 0 0
V[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 -B 0 0 A -B A 0 0 0 B 0 0 -A B -A 0 0 0 0 -B -A 0 0 0 0 -A B 0 -C -C -D 0 0 0
aeV[V ²]	0 0 A 0 0 B A B 0 0 0 -A 0 0 -B -A -B 0 0 0 0 B A 0 0 0 0 -A B 0 C -C 0 0 0 D	0 0 B 0 0 -A B -A 0 0 0 -B 0 0 A -B A 0 0 0 0 -B -A 0 0 0 0 A -B 0 -C C 0 0 -D

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	-A		-B	-A	0
0	0	-A		0	0	B		-A	B	0
-B	-A	0		-A	B	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$12.6(4) \quad 4_z 2_x 2_{xy} 1' [4_z' 2_x 2_{xy}']$$

$$4_z, 2_x 2_{xy}, \underline{1}_1$$

$$4_z 2_x 2_{xy} (2_x 2_y 2_z) \underline{1}'$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				-A	0	0						
	0	-A	0				0	A	0						
	0	0	0				0	0	0						
V[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	A	0	0
	0	0	0	0	-A	0				0	0	0	0	-A	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	0	0				0	0	A				0	B	0
	0	0	A				0	0	0				B	0	0
	0	A	0				A	0	0				0	0	0
	0	0	0				0	0	-A				0	-B	0
	0	0	-A				0	0	0				-B	0	0
	0	-A	0				-A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	A	0				0	0	0	0	-A	0
	0	0	0	0	0	B				0	0	0	0	0	-B

$[V^3]$

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	-A		-A	0	0
0	0	0		0	0	0		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

$$4_z m_x m_{xy} [4_z]$$
$$4_z m_x m_{xy} \{ 4_z \}$$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	A						-A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	C	0						
	-C	A	0				-C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	0	0	A				0	0	-B	C	0	0			
	0	0	B				0	0	A	0	C	0			
	A	B	0				-B	A	0	0	0	D			
	0	0	A				0	0	B	C	0	0			
	0	0	-B				0	0	A	0	C	0			
	A	-B	0				B	A	0	0	0	D			
	0	0	0	B	A	0				0	0	0	-B	A	0
	0	0	0	A	-B	0				0	0	0	A	B	0
	C	C	D	0	0	0				C	C	D	0	0	0
aeV[V ²]	0	0	A				0	0	-B	C	0	0			
	0	0	B				0	0	A	0	C	0			
	A	B	0				-B	A	0	0	0	D			
	0	0	-A				0	0	-B	-C	0	0			
	0	0	B				0	0	-A	0	-C	0			
	-A	B	0				-B	-A	0	0	0	-D			
	0	0	0	B	A	0				0	0	0	B	-A	0
	0	0	0	A	-B	0				0	0	0	-A	-B	0
	C	C	D	0	0	0				-C	-C	-D	0	0	0

$[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

$ae[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

$$4_z m_x m_{xy} 1' [4_z m_x m_{xy}]$$
$$4_z m_x m_{xy} \underline{1}$$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	-A	0						
	-A	0	0				A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	0	A				0	0	0	B	0	0			
	0	0	0				0	0	A	0	B	0			
	A	0	0				0	A	0	0	0	C			
	0	0	A				0	0	0	B	0	0			
	0	0	0				0	0	A	0	B	0			
	A	0	0				0	A	0	0	0	C			
	0	0	0	0	A	0				0	0	0	0	A	0
	0	0	0	A	0	0				0	0	0	A	0	0
	B	B	C	0	0	0				B	B	C	0	0	0
aeV[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

13.6(4)

 $4_{z m_x m_{xy}} 1' [4_z 'm_x' m_{xy}]$ $4_z 'm_x' m_{xy} \underline{1}'$ $4_{z m_x m_{xy}} (m_{xy} m_{xy}^{-1} 2_z) \underline{1}'$

V	0						0							
	0						0							
	A						A							
aeV	0						0							
	0						0							
	0						0							
[V ²]	A	0	0			A	0	0						
	0	A	0			0	A	0						
	0	0	B			0	0	B						
aeV ²	A	0	0			-A	0	0						
	0	-A	0			0	A	0						
	0	0	0			0	0	0						
V[V ²]	0	0	A			0	0	0			B	0	0	
	0	0	0			0	0	A			0	B	0	
	A	0	0			0	A	0			0	0	C	
	0	0	A			0	0	0			B	0	0	
	0	0	0			0	0	A			0	B	0	
	A	0	0			0	A	0			0	0	C	
	0	0	0	0	A	0			0	0	0	0	A	0
	0	0	0	A	0	0			0	0	0	A	0	0
	B	B	C	0	0	0			B	B	C	0	0	0
aeV[V ²]	0	0	A			0	0	0			B	0	0	
	0	0	0			0	0	-A			0	-B	0	
	A	0	0			0	-A	0			0	0	0	
	0	0	-A			0	0	0			-B	0	0	
	0	0	0			0	0	A			0	B	0	
	-A	0	0			0	A	0			0	0	0	
	0	0	0	0	A	0			0	0	0	0	-A	0
	0	0	0	-A	0	0			0	0	0	A	0	0
	B	-B	0	0	0	0			-B	B	0	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	-A		0	-A	0
A	0	0		0	-A	0		0	0	0
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	A		0	A	0
-A	0	0		0	A	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	-A	0			-A	A	0			

13.7(4)

 $4_{z m_x m_{xy}} 1' [4_{z m_x} m_{xy}]$ $4_{z m_x} m_{xy} \underline{1}'$ $4_{z m_x m_{xy}} (4_z) \underline{1}'$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	A						-A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				-A	0	0						
	0	A	0				0	-A	0						
	0	0	B				0	0	-B						
V[V ²]	0	0	A				0	0	0				B	0	0
	0	0	0				0	0	A				0	B	0
	A	0	0				0	A	0				0	0	C
	0	0	A				0	0	0				B	0	0
	0	0	0				0	0	A				0	B	0
	A	0	0				0	A	0				0	0	C
	0	0	0	0	A	0				0	0	0	0	A	0
	0	0	0	A	0	0				0	0	0	A	0	0
	B	B	C	0	0	0				B	B	C	0	0	0
aeV[V ²]	0	0	A				0	0	0				B	0	0
	0	0	0				0	0	A				0	B	0
	A	0	0				0	A	0				0	0	C
	0	0	-A				0	0	0				-B	0	0
	0	0	0				0	0	-A				0	-B	0
	-A	0	0				0	-A	0				0	0	-C
	0	0	0	0	A	0				0	0	0	0	-A	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	B	B	C	0	0	0				-B	-B	-C	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0	0	0	0
0	0	0		0	0	0		0	0	0
A	A	B		A	A	B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0	0	0	0
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	-A		B	-A	0
0	0	-A		0	0	-B		-A	-B	0
B	-A	0		-A	-B	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	-B	0		B	-B	0				

13.11(5) $4_{\underline{z}} m_x 'm_{xy}' [4_z]$

$4_{\underline{z}} \underline{m_x} ' \underline{m_{xy}} '$

$4_{\underline{z}} m_x m_{xy} (4_z) \{4_z\}$

V	0 0 A	0 0 A	
aeV	0 0 A	0 0 A	
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B	
aeV ²	A C 0 -C A 0 0 0 B	A -C 0 C A 0 0 0 B	
V[V ²]	0 0 A 0 0 B A B 0	0 0 -B 0 0 A -B A 0	C 0 0 0 C 0 0 0 D
	0 0 A 0 0 -B A -B 0	0 0 B 0 0 A B A 0	C 0 0 0 C 0 0 0 D
	0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 0 -B A 0 0 0 0 A B 0 C C D 0 0 0	
aeV[V ²]	0 0 A 0 0 B A B 0	0 0 -B 0 0 A -B A 0	C 0 0 0 C 0 0 0 D
	0 0 A 0 0 -B A -B 0	0 0 B 0 0 A B A 0	C 0 0 0 C 0 0 0 D
	0 0 0 B A 0 0 0 0 A -B 0 C C D 0 0 0	0 0 0 -B A 0 0 0 0 A B 0 C C D 0 0 0	

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$14.8(4) \quad \overline{4}_z 2_{x_{xy}} 1' [\overline{4}_z' 2_{x_{xy}}']$$

$$\overline{4}_z' 2_{x_{xy}}' \underline{1}'$$

$$\overline{4}_z 2_{x_{xy}} (2_x 2_y 2_z) \underline{1}'$$

V	0								0						
	0								0						
	0								0						
aeV	0								0						
	0								0						
	0								0						
[V ²]	A	0	0						A	0	0				
	0	A	0						0	A	0				
	0	0	B						0	0	B				
aeV ²	A	0	0						-A	0	0				
	0	A	0						0	-A	0				
	0	0	B						0	0	-B				
V[V ²]	0	0	0					0	0	A			0	B	0
	0	0	A					0	0	0			B	0	0
	0	A	0					A	0	0			0	0	0
	0	0	0					0	0	A			0	B	0
	0	0	A					0	0	0			B	0	0
	0	A	0					A	0	0			0	0	0
	0	0	0	A	0	0			0	0	0	A	0	0	0
	0	0	0	0	A	0			0	0	0	0	A	0	0
	0	0	0	0	0	B			0	0	0	0	0	0	B
aeV[V ²]	0	0	0					0	0	A			0	B	0
	0	0	A					0	0	0			B	0	0
	0	A	0					A	0	0			0	0	0
	0	0	0					0	0	-A			0	-B	0
	0	0	-A					0	0	0			-B	0	0
	0	-A	0					-A	0	0			0	0	0
	0	0	0	A	0	0			0	0	0	-A	0	0	0
	0	0	0	0	A	0			0	0	0	0	-A	0	0
	0	0	0	0	0	B			0	0	0	0	0	0	-B

$[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$14.9(4) \quad \overline{4}_z 2_x m_{xy} 1' [\overline{4}_z' 2_x' m_{xy}]$$

$$\overline{4}_z' 2_x' m_{xy} \underline{1}'$$

$$\overline{4}_z 2_x m_{xy} (m_{xy} m_{xy}^{-1} 2_z) \underline{1}'$$

V	0								0						
	0								0						
	0								0						
aeV	0								0						
	0								0						
	0								0						
[V ²]	A	0	0						A	0	0				
	0	A	0						0	A	0				
	0	0	B						0	0	B				
aeV ²	0	A	0						0	-A	0				
	-A	0	0						A	0	0				
	0	0	0						0	0	0				
V[V ²]	0	0	0					0	0	A			0	B	0
	0	0	A					0	0	0			B	0	0
	0	A	0					A	0	0			0	0	0
	0	0	0					0	0	A			0	B	0
	0	0	A					0	0	0			B	0	0
	0	A	0					A	0	0			0	0	0
	0	0	0	A	0	0			0	0	0	A	0	0	0
	0	0	0	0	A	0			0	0	0	0	A	0	0
	0	0	0	0	0	B			0	0	0	0	0	0	B
aeV[V ²]	0	0	A					0	0	0			B	0	0
	0	0	0					0	0	-A			0	-B	0
	A	0	0					0	-A	0			0	0	0
	0	0	-A					0	0	0			-B	0	0
	0	0	0					0	0	A			0	B	0
	-A	0	0					0	A	0			0	0	0
	0	0	0	0	A	0			0	0	0	0	-A	0	0
	0	0	0	-A	0	0			0	0	0	A	0	0	0
	B	-B	0	0	0	0			-B	B	0	0	0	0	0

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	-A		0	-A	0
A	0	0		0	-A	0		0	0	0
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	A		0	A	0
-A	0	0		0	A	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	-A	0			-A	A	0			

	$\overline{4_z}2_x'm_{xy}'1'$	$\overline{4_z}2_xm_{xy}(\overline{4_z})1'$
V	0 0 0	0 0 0
aeV	0 0 A	0 0 -A
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	0 A 0 A 0 0 0 0 0	0 -A 0 -A 0 0 0 0 0
V[V ²]	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0
	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 B	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 B
aeV[V ²]	0 0 A 0 0 0 A 0 0	0 0 0 0 0 A 0 A 0
	0 0 -A 0 0 0 -A 0 0	0 0 0 0 0 -A 0 -A 0
	0 0 0 0 A 0 0 0 0 A 0 0 B B C 0 0 0	0 0 0 0 -A 0 0 0 0 -A 0 0 -B -B -C 0 0 0

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

$$14.12(6) \quad \overline{4}_z' 2_x m_{xy}' [\overline{4}_z']$$
$$\overline{4}_z, \underline{2}_{m_{xy}}$$
$$\overline{4}_z 2_x m_{xy} (2_x 2_y 2_z) \{ \overline{4}_z (2_z) \}$$

V	0					0									
	0					0									
	0					0									
aeV	0					0									
	0					0									
	0					0									
[V ²]	A	0	0			A	0	0							
	0	A	0			0	A	0							
	0	0	B			0	0	B							
aeV ²	A	C	0			A	-C	0							
	-C	A	0			C	A	0							
	0	0	B			0	0	B							
V[V ²]	0	0	A			0	0	B		C	D	0			
	0	0	B			0	0	-A		D	-C	0			
	A	B	0			B	-A	0		0	0	0			
	0	0	-A			0	0	B		-C	D	0			
	0	0	B			0	0	A		D	C	0			
	-A	B	0			B	A	0		0	0	0			
	0	0	0	B	A	0			0	0	0	B	-A	0	
	0	0	0	-A	B	0			0	0	0	A	B	0	
	C	-C	0	0	0	D			-C	C	0	0	0	D	
aeV[V ²]	0	0	A			0	0	B		C	D	0			
	0	0	B			0	0	-A		D	-C	0			
	A	B	0			B	-A	0		0	0	0			
	0	0	-A			0	0	B		-C	D	0			
	0	0	B			0	0	A		D	C	0			
	-A	B	0			B	A	0		0	0	0			
	0	0	0	B	A	0			0	0	0	B	-A	0	
	0	0	0	-A	B	0			0	0	0	A	B	0	
	C	-C	0	0	0	D			-C	C	0	0	0	D	

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

$$14.15(6) \quad \overline{4}_z' 2_x' m_{xy} [\overline{4}_z']$$

$$\overline{4}_z' \underline{2}_x' m_{xy}$$

$$\overline{4}_z 2_x m_{xy} (m_{xy} m_{xy}^{-} 2_z) \{ \overline{4}_z (2_z) \}$$

[illegible]

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	B		0	0	-A		B	-A	0
0	0	-A		0	0	-B		-A	-B	0
B	-A	0		-A	-B	0		0	0	0
0	0	0	A	0	0	0	-A			
0	0	0		0	0	0				
B	-B	0		B	-B	0				

[V³]

0	0	B		0	0	A		B	A	0
0	0	A		0	0	-B		A	-B	0
B	A	0		A	-B	0		0	0	0
0	0	-B		0	0	A		-B	A	0
0	0	A		0	0	B		A	B	0
-B	A	0		A	B	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
B	-B	0		-B	B	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

15.3(1)

$4_z/m_z m_x m_{xy} [4_z 2_x 2_{xy}]$

$4_z/m_z m_x m_{xy}$

$4_z/m_z m_x m_{xy} \{4_z 2_x 2_{xy}\}$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				-A	0	0						
	0	A	0				0	-A	0						
	0	0	B				0	0	-B						
V[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
aeV[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	A	0	0
	0	0	0	0	-A	0				0	0	0	0	-A	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

15.5(1)

$$4_z/m_z m_x m_{xy} [\overline{4}_z 2_x m_{xy}]$$

$$\underline{4}_z/\underline{m}_z \underline{m}_x \underline{m}_{xy}$$

$$4_z/m_z m_x m_{xy} \{\overline{4}_z 2_x m_{xy}\}$$

<hr/>												
V	0							0				
	0							0				
	0							0				
aeV	0							0				
	0							0				
	0							0				
[V ²]	A	0	0					A	0	0		
	0	A	0					0	A	0		
	0	0	B					0	0	B		
aeV ²	A	0	0					-A	0	0		
	0	-A	0					0	A	0		
	0	0	0					0	0	0		
V[V ²]	0	0	0					0	0	A		
	0	0	A					0	0	0		
	0	A	0					A	0	0		
	0	0	0					0	0	-A		
	0	0	-A					0	0	0		
	0	-A	0					-A	0	0		
	0	0	0	A	0	0		0	0	0	-A	0
	0	0	0	0	A	0		0	0	0	0	-A
	0	0	0	0	0	B		0	0	0	0	0
	0	0	0					0	0	0		
	0	0	0					0	0	0		
	0	0	0					0	0	0		
aeV[V ²]	0	0	0					0	0	-A		
	0	0	A					0	0	0		
	0	A	0					-A	0	0		
	0	0	0					0	0	-A		
	0	0	A					0	0	0		
	0	A	0					-A	0	0		
	0	0	0	A	0	0		0	0	0	A	0
	0	0	0	0	-A	0		0	0	0	0	-A
	0	0	0	0	0	0		0	0	0	0	0
	0	0	0					0	0	0		
	0	0	0					0	0	0		
	0	0	0					0	0	0		

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

	$4_z/m_z, m_x, m_{xy}, \underline{1}$	$4_z/m_z, m_x, m_{xy}, (4_z, 2_x, 2_{xy}), \underline{1}$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 B 0 0 0 B	-A 0 0 0 -B 0 0 0 -B
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

15.15(4)

$$4_z/m_z m_x m_{xy} \underline{1}' [4_z/m_z 'm_x m_{xy}]$$

$$4_z/m_z 'm_x m_{xy} \underline{1}'$$

$$4_z/m_z m_x m_{xy} (4_z m_x m_{xy}) \underline{1}'$$

V	0						0					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	0						0					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	0	A	0				0	-A	0			
	-A	0	0				A	0	0			
	0	0	0				0	0	0			
V[V ²]	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
aeV[V ²]	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0				0	0	0			
	0	0	0				0	0	0			
	0	0	0				0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

	$4_z'/m_z'm_x'm_{xy}\underline{1}'$	$4_z/m_zm_xm_{xy}(\overline{4}_z2_xm_{xy})\underline{1}'$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 -A 0 0 0 0	-A 0 0 0 A 0 0 0 0
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$15.19(6) \quad 4_z/m_z m_x' m_{xy}' [4_z 2_x' 2_{xy}']$$

$$4_z / \underline{m_z m_x} \quad \underline{m_{xy}}$$

$$4_z/m_z m_x m_{xy} (4_z/m_z) \{4_z 2_x 2_{xy} (4_z)\}$$

[illegible]

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

15.21(6) $4_z/m_z m_x' m_{xy}' [\overline{4}_z 2_x' m_{xy}']$

$$\underline{4}_z / \underline{m}_z \underline{m}_x \text{ ' } m_{xy} \text{ '}$$

$$4_z/m_z m_x m_{xy} (4_z/m_z) \{ \overline{4}_z 2_x m_{xy} (\overline{4}_z) \}$$

V	0						0									
	0						0									
	0						0									
aeV	0						0									
	0						0									
	A						A									
[V ²]	A	0	0				A	0	0							
	0	A	0				0	A	0							
	0	0	B				0	0	B							
aeV ²	0	A	0				0	-A	0							
	A	0	0				-A	0	0							
	0	0	0				0	0	0							
V[V ²]	0	0	0				0	0	A				0	B	0	
	0	0	A				0	0	0				B	0	0	
	0	A	0				A	0	0				0	0	0	
	0	0	0				0	0	-A				0	-B	0	
	0	0	-A				0	0	0				-B	0	0	
	0	-A	0				-A	0	0				0	0	0	
	0	0	0	A	0	0				0	0	0	-A	0	0	
	0	0	0	0	A	0				0	0	0	0	-A	0	
	0	0	0	0	0	B				0	0	0	0	0	-B	
	aeV[V ²]	0	0	A				0	0	0				B	0	0
		0	0	0				0	0	A				0	B	0
		A	0	0				0	A	0				0	0	C
0		0	A				0	0	0				B	0	0	
0		0	0				0	0	A				0	B	0	
A		0	0				0	A	0				0	0	C	
0		0	0	0	A	0				0	0	0	0	A	0	
0		0	0	A	0	0				0	0	0	A	0	0	
B		B	C	0	0	0				B	B	C	0	0	0	

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

$$15.25(6) \quad 4_z' / m_z m_x m_{xy}' [4_z' 2_x 2_{xy}']$$

$$4_z' / \underline{m_z m_x m_{xy}}$$

$$4_z/m_z m_x m_{xy} (m_x m_y m_z) \{4_z 2_x 2_{xy} (2_x 2_y 2_z)\}$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				-A	0	0						
	0	-A	0				0	A	0						
	0	0	0				0	0	0						
V[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	0	0				0	0	A				0	B	0
	0	0	A				0	0	0				B	0	0
	0	A	0				A	0	0				0	0	0
	0	0	0				0	0	A				0	B	0
	0	0	A				0	0	0				B	0	0
	0	A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	A	0	0
	0	0	0	0	A	0				0	0	0	0	A	0
	0	0	0	0	0	B				0	0	0	0	0	B

$[V^3]$

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

15.26(6) $4_z' / m_z m_x m_{xy}' [4_z' m_x m_{xy}']$

$4_z' / \underline{m_z} m_x m_{xy}'$

$4_z / m_z m_x m_{xy} (m_x m_y m_z) \{ 4_z m_x m_{xy} (m_x m_y 2_z) \}$

V	0						0						
	0						0						
	A						-A						
aeV	0						0						
	0						0						
	0						0						
[V ²]	A	0	0				A	0	0				
	0	A	0				0	A	0				
	0	0	B				0	0	B				
aeV ²	0	A	0				0	-A	0				
	A	0	0				-A	0	0				
	0	0	0				0	0	0				
V[V ²]	0	0	A				0	0	0	B	0	0	
	0	0	0				0	0	A	0	B	0	
	A	0	0				0	A	0	0	0	C	
	0	0	-A				0	0	0	-B	0	0	
	0	0	0				0	0	-A	0	-B	0	
	-A	0	0				0	-A	0	0	0	-C	
	0	0	0	0	A	0	0	0	0	0	-A	0	
	0	0	0	A	0	0	0	0	0	-A	0	0	
	B	B	C	0	0	0	-B	-B	-C	0	0	0	
	aeV[V ²]	0	0	0				0	0	A	0	B	0
		0	0	A				0	0	0	B	0	0
		0	A	0				A	0	0	0	0	0
0		0	0				0	0	A	0	B	0	
0		0	A				0	0	0	B	0	0	
0		A	0				A	0	0	0	0	0	
0		0	0	A	0	0	0	0	0	A	0	0	
0		0	0	0	A	0	0	0	0	0	A	0	
0		0	0	0	0	B	0	0	0	0	0	B	
0		0	0				0	0	A				
0		0	A				0	0	0				
0		A	0				A	0	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
0	0	0		0	0	0				

$$15.27(6) \quad 4_z' / m_z m_x m_{xy}' [\overline{4_z'} 2_x m_{xy}']$$

	$\frac{4_z'}{m_z m_x m_{xy}'}$	$\frac{4_z}{m_z m_x m_{xy}} (m_x m_y m_z) \{ \overline{4_z} 2_x m_{xy} (2_x 2_y 2_z) \}$		
V	0	0		
	0	0		
	0	0		
aeV	0	0		
	0	0		
	0	0		
[V ²]	A 0 0	A 0 0		
	0 A 0	0 A 0		
	0 0 B	0 0 B		
aeV ²	A 0 0	-A 0 0		
	0 A 0	0 -A 0		
	0 0 B	0 0 -B		
V[V ²]	0 0 0	0 0 A	0 B 0	
	0 0 A	0 0 0	B 0 0	
	0 A 0	A 0 0	0 0 0	
	0 0 0	0 0 -A	0 -B 0	
	0 0 -A	0 0 0	-B 0 0	
	0 -A 0	-A 0 0	0 0 0	
	0 0 0 A 0 0	0 0 0 -A 0 0		
	0 0 0 0 A 0	0 0 0 0 -A 0		
	0 0 0 0 0 B	0 0 0 0 0 -B		
	aeV[V ²]	0 0 0	0 0 A	0 B 0
		0 0 A	0 0 0	B 0 0
		0 A 0	A 0 0	0 0 0
0 0 0		0 0 A	0 B 0	
0 0 A		0 0 0	B 0 0	
0 A 0		A 0 0	0 0 0	
0 0 0 A 0 0		0 0 0 A 0 0		
0 0 0 0 A 0		0 0 0 0 A 0		
0 0 0 0 0 B		0 0 0 0 0 B		

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$15.28(6) \quad 4_z' / m_z m_x m_{xy}' [\bar{4}_z' m_x 2_{xy}']$$

$$\underline{4}_z' / \underline{m}_z \underline{m}_x \underline{m}_{xy}'$$

$$4_z/m_z m_x m_{xy} (m_x m_y m_z) \{ \overline{4}_z m_x 2_{xy} (m_x m_y 2_z) \}$$

V	0						0					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	0						0					
$[V^2]$	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV^2	0	A	0				0	-A	0			
	-A	0	0				A	0	0			
	0	0	0				0	0	0			
$V[V^2]$	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	-A	0	-B	0
	A	0	0				0	-A	0	0	0	0
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	A	0	B	0
	-A	0	0				0	A	0	0	0	0
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	-A	0	0	0	0	0	0	A	0
	B	-B	0	0	0	0	-B	B	0	0	0	0
$aeV[V^2]$	0	0	0				0	0	A	0	B	0
	0	0	A				0	0	0	B	0	0
	0	A	0				A	0	0	0	0	0
	0	0	0				0	0	A	0	B	0
	0	0	A				0	0	0	B	0	0
	0	A	0				A	0	0	0	0	0
	0	0	0	A	0	0	0	0	0	A	0	0
	0	0	0	0	A	0	0	0	0	0	A	0
	0	0	0	0	0	B	0	0	0	0	0	B

$[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	-A		0	-A	0
A	0	0		0	-A	0		0	0	0
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	A		0	A	0
-A	0	0		0	A	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	-A	0		-A	A	0				

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A	0	0	0	A			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

15.30(6)

$4_z/m_z' m_x' m_{xy}' [4_z/m_z']$

$4_z/m_z' \underline{m_x}' \underline{m_{xy}}'$

$4_z/m_z m_x m_{xy} (4_z 2_x 2_{xy}) \{4_z/m_z (4_z)\}$

<hr/>													
V	0							0					
	0							0					
	0							0					
aeV	0							0					
	0							0					
	0							0					
[V ²]	A	0	0					A	0	0			
	0	A	0					0	A	0			
	0	0	B					0	0	B			
aeV ²	A	C	0					A	-C	0			
	-C	A	0					C	A	0			
	0	0	B					0	0	B			
V[V ²]	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
aeV[V ²]	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0	0	0	0		0	0	0	0	0	0
	0	0	0					0	0	0			
	0	0	0					0	0	0			
	0	0	0					0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$4_z/m_z'm_x'm_{xy}'[4_zm_x'm_{xy}']$$
$$4_z/m_zm_xm_{xy}(4_z2_x2_{xy})\{4_zm_xm_{xy}(4_z)\}$$

V	0						0					
	0						0					
	A						-A					
aeV	0						0					
	0						0					
	A						-A					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
V[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	A	0	0	0	0	0	-A	0	0
	B	B	C	0	0	0	-B	-B	-C	0	0	0
aeV[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	A	0	0	0	0	0	-A	0	0
	B	B	C	0	0	0	-B	-B	-C	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

15.34(5)

$$4_z/m_z' m_x m_{xy} [4_z m_x m_{xy}]$$

$$4_z/m_z' m_x m_{xy}$$

$$4_z/m_z m_x m_{xy} (4_z m_x m_{xy}) \{4_z m_x m_{xy}\}$$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	A	0						
	-A	0	0				-A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	0	A				0	0	0				B	0	0
	0	0	0				0	0	A				0	B	0
	A	0	0				0	A	0				0	0	C
	0	0	-A				0	0	0				-B	0	0
	0	0	0				0	0	-A				0	-B	0
	-A	0	0				0	-A	0				0	0	-C
	0	0	0	0	A	0				0	0	0	0	-A	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	B	B	C	0	0	0				-B	-B	-C	0	0	0
	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
aeV[V ²]	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$$15.35(6) \quad 4_z/m_z' m_x m_{xy} [4_z/m_z']$$

$$4_z / m_z \cdot \underline{m_x m_{xy}}$$

$$4_z/m_z m_x m_{xy} (4_z m_x m_{xy}) \{4_z/m_z (4_z)\}$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	C	0						
	-C	A	0				-C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0				0	0	0						
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	0	0				0	0	0				0	0	0
	0	0	0				0	0	0				0	0	0
	0	0	0				0	0	0				0	0	0
	0	0	0				0	0	0				0	0	0
	0	0	0				0	0	0				0	0	0
	0	0	0				0	0	0				0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

15.37(6) $4_z/m_z 'm_x m_{xy} [4_z 2_x '2_{xy} ']$

$4_z/m_z 'm_x m_{xy}$

$4_z/m_z m_x m_{xy} (4_z m_x m_{xy}) \{4_z 2_x 2_{xy} (4_z)\}$

<hr/>												
V	0							0				
	0							0				
	0							0				
aeV	0							0				
	0							0				
	A							-A				
[V ²]	A	0	0					A	0	0		
	0	A	0					0	A	0		
	0	0	B					0	0	B		
aeV ²	0	A	0					0	A	0		
	-A	0	0					-A	0	0		
	0	0	0					0	0	0		
V[V ²]	0	0	0					0	0	-A		
	0	0	A					0	0	0		
	0	A	0					-A	0	0		
	0	0	0					0	0	A		
	0	0	-A					0	0	0		
	0	-A	0					A	0	0		
	0	0	0	A	0	0		0	0	0	-A	0
	0	0	0	0	-A	0		0	0	0	0	A
	0	0	0	0	0	0		0	0	0	0	0
	0	0	A					0	0	0		
	0	0	0					0	0	A		
	A	0	0					0	A	0		
aeV[V ²]	0	0	-A					0	0	0		
	0	0	0					0	0	-A		
	-A	0	0					0	-A	0		
	0	0	0	0	A	0		0	0	0	0	-A
	0	0	0	A	0	0		0	0	0	-A	0
	B	B	C	0	0	0		-B	-B	-C	0	0
	0	0	0					0	0	0		
	0	0	0					0	0	A		
	0	0	0					0	0	0		
	0	0	0					0	0	0		
	0	0	0					0	0	0		
	0	0	0					0	0	0		

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

15.38(6) $4_z/m_z'm_{xy}[\overline{4}_z'2_x'm_{xy}]$

$$\frac{4_z}{\underline{m}_z} \frac{1}{\underline{m}_x} \frac{1}{\underline{m}_{xy}} (4_z \underline{m}_x \underline{m}_{xy}) \{ \overline{4}_z 2_x \underline{m}_{xy} (\underline{m}_{xy} \underline{m}_{xy}^{-1} 2_z) \}$$

[illegible]

$[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	$-A$		0	$-A$	0
0	0	$-A$		0	0	0		$-A$	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0	A		0	0	0	$-A$		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	$-A$		0	$-A$	0
A	0	0		0	$-A$	0		0	0	0
0	0	$-A$		0	0	0		$-A$	0	0
0	0	0		0	0	A		0	A	0
$-A$	0	0		0	A	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	$-A$	0			$-A$	A	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

	$4_z'/m_z'\underline{m}_x'\underline{m}_{xy}$	$4_z/m_zm_xm_{xy}(\overline{4}_z2_xm_{xy})\{4_z/m_z(\overline{4}_z)\}$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A B 0 B -A 0 0 0 0	A -B 0 -B -A 0 0 0 0
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$15.43(6) \quad 4_z' / m_z' m_x' m_{xy} [4_z' 2_x 2_{xy}']$$

$$4_z' / \underline{m_z'} \underline{m_x'} \underline{m_{xy}} \quad 4_z / m_z m_x m_{xy} (\overline{4_z} 2_x m_{xy}) \{4_z 2_x 2_{xy} (2_x 2_y 2_z)\}$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				A	0	0						
	0	-A	0				0	-A	0						
	0	0	0				0	0	0						
V[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	0	0				0	0	A				0	B	0
	0	0	A				0	0	0				B	0	0
	0	A	0				A	0	0				0	0	0
	0	0	0				0	0	-A				0	-B	0
	0	0	-A				0	0	0				-B	0	0
	0	-A	0				-A	0	0				0	0	0
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	A	0				0	0	0	0	-A	0
	0	0	0	0	0	B				0	0	0	0	0	-B

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

15.44(6)

$$4_z' / m_z' m_x' m_{xy} [4_z' m_x' m_{xy}]$$

$$4_z' / \underline{m_z'} m_x' m_{xy}$$

$$4_z / m_z m_x m_{xy} (\overline{4_z} 2_x m_{xy}) \{ 4_z m_x m_{xy} (m_{xy} \overline{m_{xy}} 2_z) \}$$

<hr/>														
V	0						0							
	0						0							
	A						-A							
aeV	0						0							
	0						0							
	0						0							
[V ²]	A	0	0				A	0	0					
	0	A	0				0	A	0					
	0	0	B				0	0	B					
aeV ²	A	0	0				A	0	0					
	0	-A	0				0	-A	0					
	0	0	0				0	0	0					
V[V ²]	0	0	A				0	0	0			B	0	0
	0	0	0				0	0	A			0	B	0
	A	0	0				0	A	0			0	0	C
	0	0	-A				0	0	0			-B	0	0
	0	0	0				0	0	-A			0	-B	0
	-A	0	0				0	-A	0			0	0	-C
	0	0	0	0	A	0		0	0	0	0	-A	0	
	0	0	0	A	0	0		0	0	0	-A	0	0	
	B	B	C	0	0	0		-B	-B	-C	0	0	0	
	0	0	A				0	0	0			B	0	0
	0	0	0				0	0	-A			0	-B	0
	A	0	0				0	-A	0			0	0	0
aeV[V ²]	0	0	-A				0	0	0			-B	0	0
	0	0	0				0	0	A			0	B	0
	-A	0	0				0	A	0			0	0	0
	0	0	0	0	A	0		0	0	0	0	-A	0	
	0	0	0	-A	0	0		0	0	0	A	0	0	
	B	-B	0	0	0	0		-B	B	0	0	0	0	

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	-A		0	-A	0
A	0	0		0	-A	0		0	0	0
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	A		0	A	0
-A	0	0		0	A	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	-A	0		-A	A	0				

$$15.45(6) \quad 4_z' / m_z' m_x' m_{xy} [\overline{4}_z m_x' 2_{xy}']$$

$$\underline{4}_z' / \underline{m}_z' \underline{m}_x' \underline{m}_{xy}$$

$$4_z/m_z m_x m_{xy}(\overline{4}_z 2_x m_{xy})\{\overline{4}_z m_x 2_{xy}(\overline{4}_z)\}$$

V	0 0 0	0 0 0
aeV	0 0 A	0 0 -A
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV^2	A 0 0 0 -A 0 0 0 0	A 0 0 0 -A 0 0 0 0
$V[V^2]$	0 0 A 0 0 0 A 0 0 0 0 -A 0 0 0 -A 0 0 0 0 0 0 A 0 0 0 0 -A 0 0 B -B 0 0 0 0	0 0 0 0 0 -A 0 -A 0 0 0 0 0 0 A 0 A 0 0 0 0 0 -A 0 0 0 0 A 0 0 -B B 0 0 0 0
$aeV[V^2]$	0 0 A 0 0 0 A 0 0 0 0 -A 0 0 0 -A 0 0 0 0 0 0 A 0 0 0 0 A 0 0 B B C 0 0 0	0 0 0 0 0 A 0 A 0 -B 0 0 0 -B 0 0 0 -C 0 0 0 0 -A 0 0 0 0 -A 0 0 -B -B -C 0 0 0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	-A		0	-A	0
A	0	0		0	-A	0		0	0	0
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	A		0	A	0
-A	0	0		0	A	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	-A	0		-A	A	0				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

16.1(2) $3_z 1' [3_z]$

	$3_z \underline{1}'$			$3_z \underline{1}'$		
V	0			0		
	0			0		
	A			A		
aeV	0			0		
	0			0		
	A			-A		
$[V^2]$	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	B	0	0	B
aeV ²	A	C	0	-A	-C	0
	-C	A	0	C	-A	0
	0	0	B	0	0	-B
V $[V^2]$	A	B	C	B	-A	-D
	B	-A	D	-A	-B	C
	C	D	0	-D	C	0
	A	B	C	B	-A	-D
	B	-A	D	-A	-B	C
	C	D	0	-D	C	0
	A	-A	0	D	C	B
	B	-B	0	C	-D	-A
	E	E	F	0	0	0
aeV $[V^2]$	A	B	C	B	-A	-D
	B	-A	D	-A	-B	C
	C	D	0	-D	C	0
	-A	-B	-C	-B	A	D
	-B	A	-D	A	B	-C
	-C	-D	0	D	-C	0
	A	-A	0	D	C	B
	B	-B	0	C	-D	-A
	E	E	F	0	0	0
	-A	A	0	-D	-C	-B
	-B	B	0	-C	D	A
	-E	-E	-F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D

A	-A	0	0		A	-A	0	0
B	-B	0			B	-B	0	
C	C	D			C	C	D	

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D

-A	-B	-C		-B	A	0		-C	0	0
-B	A	0		A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D

A	-A	0	0		-A	A	0	0
B	-B	0			-B	B	0	
C	C	D			-C	-C	-D	

17.1(1)

 $\overline{3}_z[3_z]$ $\underline{\underline{3}}_z$ $\overline{3}_z\{3_z\}$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	A						A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	-C	0						
	-C	A	0				C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	-A	-B	-C				-B	A	D				-E	0	0
	-B	A	-D				A	B	-C				0	-E	0
	-C	-D	0				D	-C	0				0	0	-F
	A	-A	0	D	C	B				-A	A	0	-D	-C	-B
	B	-B	0	C	-D	-A				-B	B	0	-C	D	A
	E	E	F	0	0	0				-E	-E	-F	0	0	0
	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
aeV[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	-A	0	D	C	B				A	-A	0	D	C	B
	B	-B	0	C	-D	-A				B	-B	0	C	-D	-A
	E	E	F	0	0	0				E	E	F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	-C		-B	A	0		-C	0	0
-B	A	0		A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	A	-A	0	0			
B	-B	0		B	-B	0				
C	C	D		C	C	D				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	-C		-B	A	0		-C	0	0
-B	A	0		A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	-C		-B	A	0		-C	0	0
-B	A	0		A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

18.1(1)

 $3_z 2_x [3_z]$ $3_z 2_x$ $3_z 2_x \{3_z\}$

V	0	0	
	0	0	
	A	-A	
aeV	0	0	
	0	0	
	A	-A	
[V ²]	A 0 0	A 0 0	
	0 A 0	0 A 0	
	0 0 B	0 0 B	
aeV ²	A C 0	A -C 0	
	-C A 0	C A 0	
	0 0 B	0 0 B	
V[V ²]	A B C	B -A -D	E 0 0
	B -A D	-A -B C	0 E 0
	C D 0	-D C 0	0 0 F
	A -B -C	-B -A -D	-E 0 0
	-B -A D	-A B -C	0 -E 0
	-C D 0	-D -C 0	0 0 -F
	A -A 0 D C B	A -A 0 D -C -B	
	B -B 0 C -D -A	-B B 0 -C -D -A	
	E E F 0 0 0	-E -E -F 0 0 0	
aeV[V ²]	A B C	B -A -D	E 0 0
	B -A D	-A -B C	0 E 0
	C D 0	-D C 0	0 0 F
	A -B -C	-B -A -D	-E 0 0
	-B -A D	-A B -C	0 -E 0
	-C D 0	-D -C 0	0 0 -F
	A -A 0 D C B	A -A 0 D -C -B	
	B -B 0 C -D -A	-B B 0 -C -D -A	
	E E F 0 0 0	-E -E -F 0 0 0	

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-B	-C		-B	-A	0		-C	0	0
-B	-A	0		-A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-B	-C		-B	-A	0		-C	0	0
-B	-A	0		-A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

$$18.2(2) \quad 3_z 2_x 1' [3_z 2_x]$$

$$3_z 2_x \underline{1}_y$$

$$3_z 2_x \underline{1}_y$$

V	0	0	
	0	0	
	0	0	
aeV	0	0	
	0	0	
	0	0	
[V ²]	A 0 0	A 0 0	
	0 A 0	0 A 0	
	0 0 B	0 0 B	
aeV ²	A 0 0	-A 0 0	
	0 A 0	0 -A 0	
	0 0 B	0 0 -B	
V[V ²]	A 0 0	0 -A -B	0 0 0
	0 -A B	-A 0 0	0 0 0
	0 B 0	-B 0 0	0 0 0
	A 0 0	0 -A -B	0 0 0
	0 -A B	-A 0 0	0 0 0
	0 B 0	-B 0 0	0 0 0
	A -A 0 B 0 0	A -A 0 B 0 0	
	0 0 0 0 -B -A	0 0 0 0 -B -A	
	0 0 0 0 0 0	0 0 0 0 0 0	
aeV[V ²]	A 0 0	0 -A -B	0 0 0
	0 -A B	-A 0 0	0 0 0
	0 B 0	-B 0 0	0 0 0
	-A 0 0	0 A B	0 0 0
	0 A -B	A 0 0	0 0 0
	0 -B 0	B 0 0	0 0 0
	A -A 0 B 0 0	-A A 0 -B 0 0	
	0 0 0 0 -B -A	0 0 0 0 B A	
	0 0 0 0 0 0	0 0 0 0 0 0	

$[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	$-A$	0	0		A	$-A$	0	0
0	0	0			0	0	0	
0	0	0			0	0	0	

$ae[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0

$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	$-A$	0	0		$-A$	A	0	0
0	0	0			0	0	0	
0	0	0			0	0	0	

$$18.4(4) \quad 3_z 2_x 1' [3_z 2_x']$$

$$3_z 2_x \underline{1}$$

$$3_z 2_x (3_z) \underline{1}'$$

V	0				0																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																															
---	---	--	--	--	---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

$[V^3]$

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	-A	0	0		A	-A	0	0
0	0	0			0	0	0	
0	0	0			0	0	0	

$ae[V^3]$

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C

0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C

0	0	0	0		0	0	0	0
A	-A	0			-A	A	0	
B	B	C			-B	-B	-C	

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-B	-C		-B	-A	0		-C	0	0
-B	-A	0		-A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	B	C		B	A	0		C	0	0
B	A	0		A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
C	C	D		C	C	D				

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	B	C		B	A	0		C	0	0
B	A	0		A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
C	C	D		C	C	D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-B	-C		-B	-A	0		-C	0	0
-B	-A	0		-A	B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		-B	B	0				
C	C	D		-C	-C	-D				

19.2(2) $3_{z m_x} 1' [3_{z m_x}]$

	$3_{z m_x} \underline{1}'$					$3_{z m_x} \underline{1}'$								
V	0					0								
	0					0								
	A					A								
aeV	0					0								
	0					0								
	0					0								
[V ²]	A	0	0			A	0	0						
	0	A	0			0	A	0						
	0	0	B			0	0	B						
aeV ²	0	A	0			0	-A	0						
	-A	0	0			A	0	0						
	0	0	0			0	0	0						
V[V ²]	0	A	B			A	0	0						
	A	0	0			0	-A	B						
	B	0	0			0	B	0						
	0	A	B			A	0	0						
	A	0	0			0	-A	B						
	B	0	0			0	B	0						
	0	0	0	0	B	A			0	0	0	0	B	A
	A	-A	0	B	0	0			A	-A	0	B	0	0
	C	C	D	0	0	0			C	C	D	0	0	0
aeV[V ²]	A	0	0			0	-A	-B			0	0	0	
	0	-A	B			-A	0	0			0	0	0	
	0	B	0			-B	0	0			0	0	0	
	-A	0	0			0	A	B			0	0	0	
	0	A	-B			A	0	0			0	0	0	
	0	-B	0			B	0	0			0	0	0	
	A	-A	0	B	0	0			-A	A	0	-B	0	0
	0	0	0	0	-B	-A			0	0	0	0	B	A
	0	0	0	0	0	0			0	0	0	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C

0	0	0	0		0	0	0	0		
A	-A	0			A	-A	0			
B	B	C			B	B	C			

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	-A	0	0		-A	A	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$19.4(4) \quad 3_z m_x 1' [3_z m_x']$$

	$3_z m_x' \underline{1}'$					$3_z m_x (3_z) \underline{1}'$								
V	0					0								
	0					0								
	A					A								
aeV	0					0								
	0					0								
	A					-A								
[V ²]	A	0	0			A	0	0						
	0	A	0			0	A	0						
	0	0	B			0	0	B						
aeV ²	A	0	0			-A	0	0						
	0	A	0			0	-A	0						
	0	0	B			0	0	-B						
V[V ²]	0	A	B			A	0	0	C	0	0			
	A	0	0			0	-A	B	0	C	0			
	B	0	0			0	B	0	0	0	D			
	0	A	B			A	0	0	C	0	0			
	A	0	0			0	-A	B	0	C	0			
	B	0	0			0	B	0	0	0	D			
	0	0	0	0	B	A			0	0	0	0	B	A
	A	-A	0	B	0	0			A	-A	0	B	0	0
	C	C	D	0	0	0			C	C	D	0	0	0
aeV[V ²]	0	A	B			A	0	0	C	0	0			
	A	0	0			0	-A	B	0	C	0			
	B	0	0			0	B	0	0	0	D			
	0	-A	-B			-A	0	0	-C	0	0			
	-A	0	0			0	A	-B	0	-C	0			
	-B	0	0			0	-B	0	0	0	-D			
	0	0	0	0	B	A			0	0	0	0	-B	-A
	A	-A	0	B	0	0			-A	A	0	-B	0	0
	C	C	D	0	0	0			-C	-C	-D	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		B	B	C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	B	C		B	A	0		C	0	0
B	A	0		A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
C	C	D		C	C	D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	B	C		B	A	0		C	0	0
B	A	0		A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
C	C	D		C	C	D				

20.2(1)

$\overline{3}_{z m_x} [3_{z m_x}]$

$\underline{\underline{3}}_{z m_x}$

$\overline{3}_{z m_x} \{3_{z m_x}\}$

V	0						0							
	0						0							
	A						-A							
aeV	0						0							
	0						0							
	0						0							
[V ²]	A	0	0			A	0	0						
	0	A	0			0	A	0						
	0	0	B			0	0	B						
aeV ²	0	A	0			0	-A	0						
	-A	0	0			A	0	0						
	0	0	0			0	0	0						
V[V ²]	0	A	B			A	0	0			C	0	0	
	A	0	0			0	-A	B			0	C	0	
	B	0	0			0	B	0			0	0	D	
	0	-A	-B			-A	0	0			-C	0	0	
	-A	0	0			0	A	-B			0	-C	0	
	-B	0	0			0	-B	0			0	0	-D	
	0	0	0	0	B	A			0	0	0	0	-B	-A
	A	-A	0	B	0	0			-A	A	0	-B	0	0
	C	C	D	0	0	0			-C	-C	-D	0	0	0
	aeV[V ²]	A	0	0			0	-A	-B			0	0	0
		0	-A	B			-A	0	0			0	0	0
		0	B	0			-B	0	0			0	0	0
A		0	0			0	-A	-B			0	0	0	
0		-A	B			-A	0	0			0	0	0	
0		B	0			-B	0	0			0	0	0	
A		-A	0	B	0	0			A	-A	0	B	0	0
0		0	0	0	-B	-A			0	0	0	0	-B	-A
0		0	0	0	0	0			0	0	0	0	0	0
		A	0	0			0	-A	-B			0	0	0
		0	-A	B			-A	0	0			0	0	0
		0	B	0			-B	0	0			0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	A	-A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	$-A$	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$ae[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	A	$-A$	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

	$\overline{3}_z 'm_x \underline{1}'$	$\overline{3}_z m_x (3_z m_x) \underline{1}'$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV^2	0 A 0 -A 0 0 0 0 0	0 -A 0 A 0 0 0 0 0
$V[V^2]$	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
$aeV[V^2]$	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

	$\overline{3}_z 'm_x' \underline{1}'$	$\overline{3}_z m_x (3_z 2_x) \underline{1}'$	
V	0 0 0	0 0 0	
aeV	0 0 0	0 0 0	
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B	
aeV ²	A 0 0 0 A 0 0 0 B	-A 0 0 0 -A 0 0 0 -B	
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

20.12(6) $\overline{3}_z m_x' [3_z m_x']$

	$\overline{3}_z m_x'$	$\overline{3}_z m_x(\overline{3}_z) \{ 3_z m_x(3_z) \}$
V	0 0 A	0 0 -A
aeV	0 0 A	0 0 A
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 A 0 0 0 B	-A 0 0 0 -A 0 0 0 -B
V[V ²]	0 A B A 0 0 B 0 0 0 -A -B -A 0 0 -B 0 0 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0	A 0 0 0 -A B 0 B 0 -A 0 0 0 A -B 0 -B 0 0 0 0 -A A 0 -B 0 0 -C -C -D 0 0 0
aeV[V ²]	0 A B A 0 0 B 0 0 0 A B A 0 0 B 0 0 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0	C 0 0 0 C 0 0 0 D C 0 0 0 C 0 0 0 D 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		B	B	C				

20.13(6) $\overline{3}_z m_x' [3_z 2_x']$

	$\overline{3}_z m_x'$	$\overline{3}_z m_x(\overline{3}_z)\{3_z 2_x(3_z)\}$															
V	0	0															
	0	0															
	0	0															
aeV	0	0															
	0	0															
	A	A															
[V ²]	A	0	0	A									0	0			
	0	A	0	0									A	0			
	0	0	B	0									0	B			
aeV ²	0	A	0	0									-A	0			
	-A	0	0	A									0	0			
	0	0	0	0									0	0			
V[V ²]	A	0	0	0						-A	-B	0				0	0
	0	-A	B	-A						0	0	0				0	0
	0	B	0	-B						0	0	0				0	0
	-A	0	0	0						A	B	0				0	0
	0	A	-B	A						0	0	0				0	0
	0	-B	0	B						0	0	0				0	0
	A	-A	0	B	0	0	-A						A	0	-B	0	0
	0	0	0	0	-B	-A	0						0	0	0	B	A
	0	0	0	0	0	0	0						0	0	0	0	0
	0	A	B	A						0	0	C				0	0
	A	0	0	0						-A	B	0				C	0
	B	0	0	0						B	0	0				0	D
aeV[V ²]	0	A	B	A						0	0	C				0	0
	A	0	0	0						-A	B	0				C	0
	B	0	0	0						B	0	0				0	D
	0	A	B	A						0	0	C				0	0
	A	0	0	0						-A	B	0				C	0
	B	0	0	0						B	0	0				0	D
	0	0	0	0	B	A	0						0	0	0	B	A
	A	-A	0	B	0	0	A						-A	0	B	0	0
	C	C	D	0	0	0	C						C	D	0	0	0
	0	A	B	A						0	0	C				0	0
	A	0	0	0						-A	B	0				C	0
	B	0	0	0						B	0	0				0	D

[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		B	B	C				

20.14(5) $\overline{3}_z'm_x[3_zm_x]$

	$\overline{3}_z'm_x$			$\overline{3}_zm_x(3_zm_x)\{3_zm_x\}$		
V	0			0		
	0			0		
	A			-A		
aeV	0			0		
	0			0		
	0			0		
[V ²]	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	B	0	0	B
aeV ²	0	A	0	0	A	0
	-A	0	0	-A	0	0
	0	0	0	0	0	0
V[V ²]	0	A	B	A	0	0
	A	0	0	0	-A	B
	B	0	0	0	B	0
	0	-A	-B	-A	0	0
	-A	0	0	0	A	-B
	-B	0	0	0	-B	0
	0	0	0	0	0	0
	A	-A	0	-A	A	0
	C	C	D	-C	-C	-D
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
aeV[V ²]	A	0	0	0	-A	-B
	0	-A	B	-A	0	0
	0	B	0	-B	0	0
	-A	0	0	0	A	B
	0	A	-B	A	0	0
	0	-B	0	B	0	0
	A	-A	0	-A	A	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

20.16(6) $\overline{3}_z 'm_x [3_z 2_x ']$

	$\overline{3}_z, \underline{m}_x$	$\overline{3}_z m_x (3_z m_x) \{3_z 2_x (3_z)\}$
V	0 0 0	0 0 0
aeV	0 0 A	0 0 -A
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	0 A 0 -A 0 0 0 0 0	0 A 0 -A 0 0 0 0 0
V[V ²]	A 0 0 0 -A B 0 B 0 -A 0 0 0 A -B 0 -B 0 A -A 0 B 0 0 0 0 0 0 -B -A 0 0 0 0 0 0	0 -A -B -A 0 0 -B 0 0 0 A B A 0 0 B 0 0 -A A 0 -B 0 0 0 0 0 0 B A 0 0 0 0 0 0
aeV[V ²]	0 A B A 0 0 B 0 0 0 -A -B -A 0 0 -B 0 0 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0	A 0 0 0 -A B 0 B 0 -A 0 0 0 A -B 0 -B 0 0 0 0 0 -B -A -A A 0 -B 0 0 -C -C -D 0 0 0

[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

$[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	$-A$	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$ae[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	$-A$	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$$20.18(6) \quad \overline{3}_z' m_x' [\overline{3}_z']$$

$$\overline{3}_z \text{ ' } \underline{\underline{m}}_x \text{ '}$$

$$\overline{3}_z m_x (3_z 2_x) \{ \overline{3}_z (3_z) \}$$

[illegible]

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

20.19(6) $\overline{3}_z'm_x'[3_zm_x']$

$\overline{3}_z'm_x'$

$\overline{3}_zm_x(3_z2_x)\{3_zm_x(3_z)\}$

V	0						0									
	0						0									
	A						-A									
aeV	0						0									
	0						0									
	A						-A									
[V ²]	A	0	0			A	0	0								
	0	A	0			0	A	0								
	0	0	B			0	0	B								
aeV ²	A	0	0			A	0	0								
	0	A	0			0	A	0								
	0	0	B			0	0	B								
V[V ²]	0	A	B			A	0	0			C	0	0			
	A	0	0			0	-A	B			0	C	0			
	B	0	0			0	B	0			0	0	D			
	0	-A	-B			-A	0	0			-C	0	0			
	-A	0	0			0	A	-B			0	-C	0			
	-B	0	0			0	-B	0			0	0	-D			
	0	0	0	0	B	A					0	0	0	0	-B	-A
	A	-A	0	B	0	0					-A	A	0	-B	0	0
	C	C	D	0	0	0					-C	-C	-D	0	0	0
	aeV[V ²]	0	A	B			A	0	0			C	0	0		
		A	0	0			0	-A	B			0	C	0		
		B	0	0			0	B	0			0	0	D		
0		-A	-B			-A	0	0			-C	0	0			
-A		0	0			0	A	-B			0	-C	0			
-B		0	0			0	-B	0			0	0	-D			
0		0	0	0	B	A					0	0	0	0	-B	-A
A		-A	0	B	0	0					-A	A	0	-B	0	0
C		C	D	0	0	0					-C	-C	-D	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	-B		-A	0	0		-B	0	0
-A	0	0		0	A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		-B	-B	-C				

21.1(1)

$6_z[3_z]$

$\underline{6_z}$

$6_z\{3_z\}$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	A						A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				A	C	0						
	-C	A	0				-C	A	0						
	0	0	B				0	0	B						
V[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	-A	-B	C				-B	A	-D				E	0	0
	-B	A	D				A	B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	-A	0	D	C	B				-A	A	0	D	C	-B
	B	-B	0	C	-D	-A				-B	B	0	C	-D	A
	E	E	F	0	0	0				E	E	F	0	0	0
	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
aeV[V ²]	-A	-B	C				-B	A	-D				E	0	0
	-B	A	D				A	B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	-A	0	D	C	B				-A	A	0	D	C	-B
	B	-B	0	C	-D	-A				-B	B	0	C	-D	A
	E	E	F	0	0	0				E	E	F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	C		-B	A	0		C	0	0
-B	A	0		A	B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		C	C	D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	C		-B	A	0		C	0	0
-B	A	0		A	B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		C	C	D				

$[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0	0	0	0
0	0	0		0	0	0		0	0	0
A	A	B		A	A	B				

$ae[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0	0	0	0
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

$6_z' [3_z]$
$$6_z (3_z) \{3_z\}$$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	A						-A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	-C	0						
	-C	A	0				C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	-A	-B	C				-B	A	-D				E	0	0
	-B	A	D				A	B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	-A	0	D	C	B				-A	A	0	D	C	-B
	B	-B	0	C	-D	-A				-B	B	0	C	-D	A
	E	E	F	0	0	0				E	E	F	0	0	0
aeV[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	B	-C				B	-A	D				-E	0	0
	B	-A	-D				-A	-B	-C				0	-E	0
	-C	-D	0				D	-C	0				0	0	-F
	A	-A	0	D	C	B				A	-A	0	-D	-C	B
	B	-B	0	C	-D	-A				B	-B	0	-C	D	-A
	E	E	F	0	0	0				-E	-E	-F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	C		-B	A	0		C	0	0
-B	A	0		A	B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		C	C	D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	B	-C		B	-A	0		-C	0	0
B	-A	0		-A	-B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		B	-B	0				
C	C	D		-C	-C	-D				

22.1(1)

$\overline{6}_z[3_z]$

$\underline{\overline{6}}_z$

$\overline{6}_z\{3_z\}$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	A						A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	-C	0						
	-C	A	0				C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	B	-C				B	-A	D				-E	0	0
	B	-A	-D				-A	-B	-C				0	-E	0
	-C	-D	0				D	-C	0				0	0	-F
	A	-A	0	D	C	B				A	-A	0	-D	-C	B
	B	-B	0	C	-D	-A				B	-B	0	-C	D	-A
	E	E	F	0	0	0				-E	-E	-F	0	0	0
	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
aeV[V ²]	-A	-B	C				-B	A	-D				E	0	0
	-B	A	D				A	B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	-A	0	D	C	B				-A	A	0	D	C	-B
	B	-B	0	C	-D	-A				-B	B	0	C	-D	A
	E	E	F	0	0	0				E	E	F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	B	-C		B	-A	0		-C	0	0
B	-A	0		-A	-B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		B	-B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
-A	-B	C		-B	A	0		C	0	0
-B	A	0		A	B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	-A	0	0	-A	A	0	0			
B	-B	0		-B	B	0				
C	C	D		C	C	D				

[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0

A	-A	0	0		A	-A	0	0
B	-B	0			B	-B	0	
0	0	0			0	0	0	

ae[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0

-A	-B	0		-B	A	0		0	0	0
-B	A	0		A	B	0		0	0	0
0	0	0		0	0	0		0	0	0

A	-A	0	0		-A	A	0	0
B	-B	0			-B	B	0	
0	0	0			0	0	0	

22.5(5)

 $\overline{6}_z' [3_z]$ $\overline{6}_z'$ $\overline{6}_z(3_z)\{3_z\}$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	A						-A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				A	C	0						
	-C	A	0				-C	A	0						
	0	0	B				0	0	B						
V[V ²]	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
	A	B	-C				B	-A	D				-E	0	0
	B	-A	-D				-A	-B	-C				0	-E	0
	-C	-D	0				D	-C	0				0	0	-F
	A	-A	0	D	C	B				A	-A	0	-D	-C	B
	B	-B	0	C	-D	-A				B	-B	0	-C	D	-A
	E	E	F	0	0	0				-E	-E	-F	0	0	0
	A	B	C				B	-A	-D				E	0	0
	B	-A	D				-A	-B	C				0	E	0
	C	D	0				-D	C	0				0	0	F
aeV[V ²]	A	B	-C				B	-A	D				-E	0	0
	B	-A	-D				-A	-B	-C				0	-E	0
	-C	-D	0				D	-C	0				0	0	-F
	A	-A	0	D	C	B				A	-A	0	-D	-C	B
	B	-B	0	C	-D	-A				B	-B	0	-C	D	-A
	E	E	F	0	0	0				-E	-E	-F	0	0	0

[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	B	-C		B	-A	0		-C	0	0
B	-A	0		-A	-B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		B	-B	0				
C	C	D		-C	-C	-D				

ae[V³]

A	B	C		B	-A	0		C	0	0
B	-A	0		-A	-B	C		0	C	0
C	0	0		0	C	0		0	0	D
A	B	-C		B	-A	0		-C	0	0
B	-A	0		-A	-B	-C		0	-C	0
-C	0	0		0	-C	0		0	0	-D
A	-A	0	0	A	-A	0	0			
B	-B	0		B	-B	0				
C	C	D		-C	-C	-D				

23.1(1)

$6_z/m_z[6_z]$

$6_z/\underline{m}_z$

$6_z/m_z\{6_z\}$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	A						A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				-A	-C	0						
	-C	A	0				C	-A	0						
	0	0	B				0	0	-B						
V[V ²]	0	0	A				0	0	-B				C	0	0
	0	0	B				0	0	A				0	C	0
	A	B	0				-B	A	0				0	0	D
	0	0	-A				0	0	B				-C	0	0
	0	0	-B				0	0	-A				0	-C	0
	-A	-B	0				B	-A	0				0	0	-D
	0	0	0	B	A	0				0	0	0	-B	-A	0
	0	0	0	A	-B	0				0	0	0	-A	B	0
	C	C	D	0	0	0				-C	-C	-D	0	0	0
	0	0	A				0	0	-B				C	0	0
	0	0	B				0	0	A				0	C	0
	A	B	0				-B	A	0				0	0	D
	0	0	A				0	0	-B				C	0	0
	0	0	B				0	0	A				0	C	0
	A	B	0				-B	A	0				0	0	D
aeV[V ²]	0	0	0	B	A	0				0	0	0	B	A	0
	0	0	0	A	-B	0				0	0	0	A	-B	0
	C	C	D	0	0	0				C	C	D	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

23.11(5) $6_z/m_z' [6_z]$

	$6_z/\underline{m}_z$			$6_z/m_z(6_z)\{6_z\}$								
V	0			0								
	0			0								
	A			-A								
aeV	0			0								
	0			0								
	A			-A								
[V ²]	A	0	0	A	0	0						
	0	A	0	0	A	0						
	0	0	B	0	0	B						
aeV ²	A	C	0	A	C	0						
	-C	A	0	-C	A	0						
	0	0	B	0	0	B						
V[V ²]	0	0	A	0	0	-B	C	0	0			
	0	0	B	0	0	A	0	C	0			
	A	B	0	-B	A	0	0	0	D			
	0	0	-A	0	0	B	-C	0	0			
	0	0	-B	0	0	-A	0	-C	0			
	-A	-B	0	B	-A	0	0	0	-D			
	0	0	0	B	A	0	0	0	0	-B	-A	0
	0	0	0	A	-B	0	0	0	0	-A	B	0
	C	C	D	0	0	0	-C	-C	-D	0	0	0
	0	0	A	0	0	-B	C	0	0			
	0	0	B	0	0	A	0	C	0			
	A	B	0	-B	A	0	0	0	D			
aeV[V ²]	0	0	-A	0	0	B	-C	0	0			
	0	0	-B	0	0	-A	0	-C	0			
	-A	-B	0	B	-A	0	0	0	-D			
	0	0	0	B	A	0	0	0	0	-B	-A	0
	0	0	0	A	-B	0	0	0	0	-A	B	0
	C	C	D	0	0	0	-C	-C	-D	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

$$23.12(6) \quad \underline{6}_z/m_z' [\overline{6}_z']$$

	$\underline{6}_z/\mathrm{m}_z'$	$\underline{6}_z/\mathrm{m}_z(\underline{6}_z)\{\overline{6}_z(3_z)\}$	
V	0	0	
	0	0	
	0	0	
aeV	0	0	
	0	0	
	0	0	
[V ²]	A 0 0	A 0 0	
	0 A 0	0 A 0	
	0 0 B	0 0 B	
aeV ²	A C 0	A C 0	
	-C A 0	-C A 0	
	0 0 B	0 0 B	
V[V ²]	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	-A -B 0	-B A 0	0 0 0
	-B A 0	A B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	A -A 0 0 0 B	-A A 0 0 0 -B	
	B -B 0 0 0 -A	-B B 0 0 0 A	
	0 0 0 0 0 0	0 0 0 0 0 0	
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	-A -B 0	-B A 0	0 0 0
	-B A 0	A B 0	0 0 0
	0 0 0	0 0 0	0 0 0
aeV[V ²]	A -A 0 0 0 B	-A A 0 0 0 -B	
	B -B 0 0 0 -A	-B B 0 0 0 A	
	0 0 0 0 0 0	0 0 0 0 0 0	
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	-A -B 0	-B A 0	0 0 0
	-B A 0	A B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	A -A 0 0 0 B	-A A 0 0 0 -B	
	B -B 0 0 0 -A	-B B 0 0 0 A	
	0 0 0 0 0 0	0 0 0 0 0 0	
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0

[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	-B	0		-B	A	0		0	0	0
-B	A	0		A	B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0		-A	A	0	0		
B	-A	0			-B	B	0			
0	0	0			0	0	0			

ae[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	-B	0		-B	A	0		0	0	0
-B	A	0		A	B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0		-A	A	0	0		
B	-B	0			-B	B	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

23.19(6) $6_z'/m_z'[\overline{6}_z']$

	$\underline{6}_z'/m_z'$	$6_z/m_z(\overline{3}_z)\{\overline{6}_z(3_z)\}$	
V	0	0	
	0	0	
	0	0	
aeV	0	0	
	0	0	
	0	0	
[V ²]	A 0 0	A 0 0	
	0 A 0	0 A 0	
	0 0 B	0 0 B	
aeV ²	A C 0	-A -C 0	
	-C A 0	C -A 0	
	0 0 B	0 0 -B	
V[V ²]	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	-A -B 0	-B A 0	0 0 0
	-B A 0	A B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	A -A 0 0 0 B	-A A 0 0 0 -B	
	B -B 0 0 0 -A	-B B 0 0 0 A	
	0 0 0 0 0 0	0 0 0 0 0 0	
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
aeV[V ²]	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0
	A -A 0 0 0 B	A -A 0 0 0 B	
	B -B 0 0 0 -A	B -B 0 0 0 -A	
	0 0 0 0 0 0	0 0 0 0 0 0	
	A B 0	B -A 0	0 0 0
	B -A 0	-A -B 0	0 0 0
	0 0 0	0 0 0	0 0 0

[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	-B	0		-B	A	0		0	0	0
-B	A	0		A	B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0		-A	A	0	0		
B	-A	0			-B	B	0			
0	0	0			0	0	0			

ae[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0		A	-A	0	0		
B	-B	0			B	-B	0			
0	0	0			0	0	0			

[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$24.7(4) \quad 6_z 2_x 2_1 1' [6_z 2_x' 2_1']$$

	$6_z 2_x' 2_1' \underline{1}'$						$6_z 2_x 2_1 (6_z) \underline{1}'$						
V	0						0						
	0						0						
	0						0						
aeV	0						0						
	0						0						
	A						-A						
[V ²]	A	0	0				A	0	0				
	0	A	0				0	A	0				
	0	0	B				0	0	B				
aeV ²	0	A	0				0	-A	0				
	-A	0	0				A	0	0				
	0	0	0				0	0	0				
V[V ²]	0	0	0				0	0	-A		0	0	0
	0	0	A				0	0	0		0	0	0
	0	A	0				-A	0	0		0	0	0
	0	0	0				0	0	-A		0	0	0
	0	0	A				0	0	0		0	0	0
	0	A	0				-A	0	0		0	0	0
	0	0	0	A	0	0		0	0	0	A	0	0
	0	0	0	0	-A	0		0	0	0	0	-A	0
	0	0	0	0	0	0		0	0	0	0	0	0
aeV[V ²]	0	0	A				0	0	0		B	0	0
	0	0	0				0	0	A		0	B	0
	A	0	0				0	A	0		0	0	C
	0	0	-A				0	0	0		-B	0	0
	0	0	0				0	0	-A		0	-B	0
	-A	0	0				0	-A	0		0	0	-C
	0	0	0	0	A	0		0	0	0	0	-A	0
	0	0	0	A	0	0		0	0	0	-A	0	0
	B	B	C	0	0	0		-B	-B	-C	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

24.8(5)

$6_z'2_x2_1'[3_z2_x]$

$\underline{6_z'2_x2_1'}$

$6_z2_x2_1(3_z2_x)\{3_z2_x\}$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				-A	0	0						
	0	A	0				0	-A	0						
	0	0	B				0	0	-B						
V[V ²]	A	0	0				0	-A	-B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	-A	0	0				0	A	-B				0	0	0
	0	A	B				A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	A	-A	0	B	0	0				-A	A	0	B	0	0
	0	0	0	0	-B	-A				0	0	0	0	-B	A
	0	0	0	0	0	0				0	0	0	0	0	0
	A	0	0				0	-A	-B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
aeV[V ²]	A	0	0				0	-A	B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	A	0	0				0	-A	B				0	0	0
	0	-A	-B				-A	0	0				0	0	0
	0	-B	0				B	0	0				0	0	0
	A	-A	0	B	0	0				A	-A	0	-B	0	0
	0	0	0	0	-B	-A				0	0	0	0	B	-A
	0	0	0	0	0	0				0	0	0	0	0	0
	A	0	0				0	-A	-B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0

$[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	$-A$	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$ae[V^3]$

A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	$-A$	0	0	A	$-A$	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	-A	0		-A	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0	0	0	0	0	0	0	0
A	-A	0		-A	A	0				
0	0	0		0	0	0				

ae[V³]

-A	0	B		0	A	0		B	0	0
0	A	0		A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
-A	0	-B		0	A	0		-B	0	0
0	A	0		A	0	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
-A	A	0	0	-A	A	0	0			
0	0	0		0	0	0				
B	B	C		-B	-B	-C				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

$$24.12(6) \quad 6_z 2_x' 2_1' [3_z 2_x']$$
$$\underline{6}_z 2_x ' \underline{2}_1 '$$
$$6_z 2_x 2_1 (6_z) \{ 3_z 2_x (3_z) \}$$

V	0						0					
	0						0					
	0						0					
aeV	0						0					
	0						0					
	A						A					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	0	A	0				0	A	0			
	-A	0	0				-A	0	0			
	0	0	0				0	0	0			
V[V ²]	A	0	0				0	-A	-B			
	0	-A	B				-A	0	0			
	0	B	0				-B	0	0			
	-A	0	0				0	A	-B			
	0	A	B				A	0	0			
	0	B	0				-B	0	0			
	A	-A	0	B	0	0	-A	A	0	B	0	0
	0	0	0	0	-B	-A	0	0	0	0	-B	A
	0	0	0	0	0	0	0	0	0	0	0	0
aeV[V ²]	0	A	B				A	0	0			
	A	0	0				0	-A	B			
	B	0	0				0	B	0			
	0	-A	B				-A	0	0			
	-A	0	0				0	A	B			
	B	0	0				0	B	0			
	0	0	0	0	B	A	0	0	0	0	B	-A
	A	-A	0	B	0	0	-A	A	0	B	0	0
	C	C	D	0	0	0	C	C	D	0	0	0

[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

25.1(1)

$6_{z m_x m_1} [3_{z m_x}]$

$6_{z m_x m_1}$

$6_{z m_x m_1} \{3_{z m_x}\}$

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	A	0						
	-A	0	0				-A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	A	B				A	0	0				C	0	0
	A	0	0				0	-A	B				0	C	0
	B	0	0				0	B	0				0	0	D
	0	-A	B				-A	0	0				C	0	0
	-A	0	0				0	A	B				0	C	0
	B	0	0				0	B	0				0	0	D
	0	0	0	0	B	A				0	0	0	0	B	-A
	A	-A	0	B	0	0				-A	A	0	B	0	0
	C	C	D	0	0	0				C	C	D	0	0	0
	A	0	0				0	-A	-B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
aeV[V ²]	-A	0	0				0	A	-B				0	0	0
	0	A	B				A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	A	-A	0	B	0	0				-A	A	0	B	0	0
	0	0	0	0	-B	-A				0	0	0	0	-B	A
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

$$6_{\text{z}}\text{m}_{\text{x}}\text{m}_11' [6_{\text{z}}\text{m}_{\text{x}}\text{m}_1]$$
 $6_z m_x m_1 \underline{1}$ '

V	0						0								
	0						0								
	A						A								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	-A	0						
	-A	0	0				A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	0	A				0	0	0	B	0	0			
	0	0	0				0	0	A	0	B	0			
	A	0	0				0	A	0	0	0	C			
	0	0	A				0	0	0	B	0	0			
	0	0	0				0	0	A	0	B	0			
	A	0	0				0	A	0	0	0	C			
	0	0	0	0	A	0		0	0	0	0	A	0		
	0	0	0	A	0	0		0	0	0	A	0	0		
	B	B	C	0	0	0		B	B	C	0	0	0		
aeV[V ²]	0	0	0				0	0	-A				0	0	0
	0	0	A				0	0	0				0	0	0
	0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	A				0	0	0
	0	0	-A				0	0	0				0	0	0
	0	-A	0				A	0	0				0	0	0
	0	0	0	A	0	0		0	0	0	-A	0	0		
	0	0	0	0	-A	0		0	0	0	0	A	0		
	0	0	0	0	0	0		0	0	0	0	0	0		

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			
0	0	0			0	0	0			

$$6_{\text{z}}\text{m}_{\text{x}}\text{m}_1\text{1}'[6_{\text{z}}\text{m}_{\text{x}}'\text{m}_1']$$
$$6_z m_x m_1 (6_z) \underline{1}$$

V	0						0					
	0						0					
	A						A					
aeV	0						0					
	0						0					
	A						-A					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	A	0	0				-A	0	0			
	0	A	0				0	-A	0			
	0	0	B				0	0	-B			
V[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	0	0	A	0	0	0	0	0	A	0
	0	0	0	A	0	0	0	0	0	0	A	0
	B	B	C	0	0	0	0	0	B	B	C	0
aeV[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	0	-A
	0	0	0	A	0	0	0	0	0	0	-A	0
	B	B	C	0	0	0	0	0	-B	-B	-C	0

$[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

$ae[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

25.8(5)

$6_z 'm_x m_1' [3_z m_x]$

$6_z 'm_x m_1'$

$6_z m_x m_1 (3_z m_x) \{3_z m_x\}$

<hr/>														
V	0													
	0													
	A													
<hr/>														
aeV	0													
	0													
	0													
<hr/>														
[V ²]	A	0	0											
	0	A	0											
	0	0	B											
<hr/>														
aeV ²	0	A	0											
	-A	0	0											
	0	0	0											
<hr/>														
V[V ²]	0	A	B				A	0	0			C	0	0
	A	0	0				0	-A	B			0	C	0
	B	0	0				0	B	0			0	0	D
	0	-A	B				-A	0	0			C	0	0
	-A	0	0				0	A	B			0	C	0
	B	0	0				0	B	0			0	0	D
	0	0	0	0	B	A						0	0	0
	A	-A	0	B	0	0						-A	A	0
	C	C	D	0	0	0						C	C	D
	0	0	0	0	0	0						0	0	0
	0	-A	B	0	0	0						0	0	0
	0	B	0	0	0	0						0	0	0
<hr/>														
aeV[V ²]	A	0	0				0	-A	-B			0	0	0
	0	-A	B				-A	0	0			0	0	0
	0	B	0				-B	0	0			0	0	0
	A	0	0				0	-A	B			0	0	0
	0	-A	-B				-A	0	0			0	0	0
	0	-B	0				B	0	0			0	0	0
	A	-A	0	B	0	0						A	-A	0
	0	0	0	0	-B	-A						0	0	0
	0	0	0	0	0	0						0	0	0
	0	0	0	0	0	0						0	0	0
	0	0	0	0	0	0						0	0	0
	0	0	0	0	0	0						0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	A	-A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

25.9(6)

$6_z 'm_x m_1' [3_z m_1']$

$\underline{6}_z 'm_x m_1'$

$6_z m_x m_1 (3_z m_x) \{3_z m_1 (3_z)\}$

<hr/>											
V	0							0			
	0							0			
	A							A			
aeV	0							0			
	0							0			
	A							-A			
[V ²]	A	0	0					A	0	0	
	0	A	0					0	A	0	
	0	0	B					0	0	B	
aeV ²	A	0	0					-A	0	0	
	0	A	0					0	-A	0	
	0	0	B					0	0	-B	
V[V ²]	-A	0	B					0	A	0	
	0	A	0					A	0	B	
	B	0	0					0	B	0	
	A	0	B					0	-A	0	
	0	-A	0					-A	0	B	
	B	0	0					0	B	0	
	-A	A	0	0	B	0		A	-A	0	0
	0	0	0	B	0	A		0	0	0	B
	C	C	D	0	0	0		C	C	D	0
aeV[V ²]	-A	0	B					0	A	0	
	0	A	0					A	0	B	
	B	0	0					0	B	0	
	-A	0	-B					0	A	0	
	0	A	0					A	0	-B	
	-B	0	0					0	-B	0	
	-A	A	0	0	B	0		-A	A	0	0
	0	0	0	B	0	A		0	0	0	-B
	C	C	D	0	0	0		-C	-C	-D	0

[V³]

-A	0	B		0	A	0		B	0	0
0	A	0		A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
A	0	B		0	-A	0		B	0	0
0	-A	0		-A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
-A	A	0	0		A	-A	0	0		
0	0	0			0	0	0			
B	B	C			B	B	C			

ae[V³]

-A	0	B		0	A	0		B	0	0
0	A	0		A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
-A	0	-B		0	A	0		-B	0	0
0	A	0		A	0	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
-A	A	0	0		-A	A	0	0		
0	0	0			0	0	0			
B	B	C			-B	-B	-C			

25.11(5) $6_z m_x 'm_1' [6_z]$

	$6_z \underline{m}_x \text{ ' } \underline{m}_1 \text{ '}$			$6_z m_x m_1 (6_z) \{6_z\}$					
V	0			0					
	0			0					
	A			A					
aeV	0			0					
	0			0					
	A			A					
[V ²]	A	0	0	A	0	0			
	0	A	0	0	A	0			
	0	0	B	0	0	B			
aeV ²	A	C	0	A	-C	0			
	-C	A	0	C	A	0			
	0	0	B	0	0	B			
V[V ²]	0	0	A	0	0	-B	C	0	0
	0	0	B	0	0	A	0	C	0
	A	B	0	-B	A	0	0	0	D
	0	0	A	0	0	B	C	0	0
	0	0	-B	0	0	A	0	C	0
	A	-B	0	B	A	0	0	0	D
	0	0	0	B	A	0	0	0	0
	0	0	0	A	-B	0	0	0	0
	C	C	D	0	0	0	C	C	D
	0	0	0	0	0	-B	A	0	0
	0	0	0	A	-B	0	0	0	0
	C	C	D	0	0	0	C	C	D
aeV[V ²]	0	0	A	0	0	-B	C	0	0
	0	0	B	0	0	A	0	C	0
	A	B	0	-B	A	0	0	0	D
	0	0	A	0	0	B	C	0	0
	0	0	-B	0	0	A	0	C	0
	A	-B	0	B	A	0	0	0	D
	0	0	0	B	A	0	0	0	0
	0	0	0	A	-B	0	0	0	0
	C	C	D	0	0	0	C	C	D
	0	0	0	0	0	-B	A	0	0
	0	0	0	A	-B	0	0	0	0
	C	C	D	0	0	0	C	C	D

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

25.12(6) $6_z m_x 'm_1' [3_z m_x ']$

	$\underline{6_z m_x} \text{ ' } \underline{m_1} \text{ '}$					$\underline{6_z m_x m_1} (\underline{6_z}) \{ \underline{3_z m_x} (\underline{3_z}) \}$									
V	0					0									
	0					0									
	A					A									
aeV	0					0									
	0					0									
	A					A									
[V ²]	A	0	0			A	0	0							
	0	A	0			0	A	0							
	0	0	B			0	0	B							
aeV ²	A	0	0			A	0	0							
	0	A	0			0	A	0							
	0	0	B			0	0	B							
V[V ²]	0	A	B			A	0	0			C	0	0		
	A	0	0			0	-A	B			0	C	0		
	B	0	0			0	B	0			0	0	D		
	0	-A	B			-A	0	0			C	0	0		
	-A	0	0			0	A	B			0	C	0		
	B	0	0			0	B	0			0	0	D		
	0	0	0	0	B	A			0	0	0	0	B	-A	
	A	-A	0	B	0	0			-A	A	0	B	0	0	
	C	C	D	0	0	0			C	C	D	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	
aeV[V ²]	0	A	B			A	0	0			C	0	0		
	A	0	0			0	-A	B			0	C	0		
	B	0	0			0	B	0			0	0	D		
	0	-A	B			-A	0	0			C	0	0		
	-A	0	0			0	A	B			0	C	0		
	B	0	0			0	B	0			0	0	D		
	0	0	0	0	B	A			0	0	0	0	B	-A	
	A	-A	0	B	0	0			-A	A	0	B	0	0	
	C	C	D	0	0	0			C	C	D	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	
	0	0	0	0	0	0			0	0	0	0	0	0	

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

$$26.1(1) \quad \overline{6}_z m_x 2_1 [3_z 2_1]$$

$$\overline{\overline{6}}_{\underline{z}\underline{x}}2_1 \quad \overline{6}_{\underline{z}\underline{x}}2_1\{3_{\underline{z}}2_1\}$$

V	0 0 0		0 0 0
aeV	0 0 0		0 0 0
[V ²]	A 0 0 0 A 0 0 0 B		A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 A 0 0 0 B		-A 0 0 0 -A 0 0 0 -B
V[V ²]	0 A 0 A 0 B 0 B 0	A 0 -B 0 -A 0 -B 0 0	0 0 0 0 0 0 0 0 0
	0 A 0 A 0 -B 0 -B 0	A 0 B 0 -A 0 B 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 B 0 A A -A 0 0 -B 0 0 0 0 0 0 0		0 0 0 -B 0 A A -A 0 0 B 0 0 0 0 0 0 0
aeV[V ²]	0 A 0 A 0 B 0 B 0	A 0 -B 0 -A 0 -B 0 0	0 0 0 0 0 0 0 0 0
	0 -A 0 -A 0 B 0 B 0	-A 0 -B 0 A 0 -B 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 B 0 A A -A 0 0 -B 0 0 0 0 0 0 0		0 0 0 B 0 -A -A A 0 0 -B 0 0 0 0 0 0 0

$[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	0	0	0		0	0	0	0
A	-A	0			A	-A	0	
0	0	0			0	0	0	

$ae[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	-A	0		-A	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	0	0	0		0	0	0	0
A	-A	0			-A	A	0	
0	0	0			0	0	0	

26.2(1)

$\overline{6}_{z m_x 2_1} [3_{z m_x}]$

$\overline{6}_{z m_x 2_1}$

$\overline{6}_{z m_x 2_1} \{3_{z m_x}\}$

V	0						0								
	0						0								
	A						-A								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	-A	0						
	-A	0	0				A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	A	B				A	0	0				C	0	0
	A	0	0				0	-A	B				0	C	0
	B	0	0				0	B	0				0	0	D
	0	A	-B				A	0	0				-C	0	0
	A	0	0				0	-A	-B				0	-C	0
	-B	0	0				0	-B	0				0	0	-D
	0	0	0	0	B	A				0	0	0	0	-B	A
	A	-A	0	B	0	0				A	-A	0	-B	0	0
	C	C	D	0	0	0				-C	-C	-D	0	0	0
	0	0	0				0	-A	-B				0	0	0
	0	-A	B				-A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
aeV[V ²]	-A	0	0				0	A	-B				0	0	0
	0	A	B				A	0	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	A	-A	0	B	0	0				-A	A	0	B	0	0
	0	0	0	0	-B	-A				0	0	0	0	-B	A
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	-B		A	0	0		-B	0	0
A	0	0		0	-A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		-B	-B	-C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

$$26.8(4) \quad \overline{6}_z m_x 2_1 1' [\overline{6}_z 'm_x' 2_1]$$

	$\overline{6}_z 'm_x' 2_1 \underline{1}'$					$\overline{6}_z m_x 2_1 (3_z 2_1) \underline{1}'$				
V	0					0				
	0					0				
	0					0				
aeV	0					0				
	0					0				
	0					0				
[V ²]	A	0	0			A	0	0		
	0	A	0			0	A	0		
	0	0	B			0	0	B		
aeV ²	A	0	0			-A	0	0		
	0	A	0			0	-A	0		
	0	0	B			0	0	-B		
V[V ²]	0	A	0			A	0	0		0
	A	0	0			0	-A	0		0
	0	0	0			0	0	0		0
	0	A	0			A	0	0		0
	A	0	0			0	-A	0		0
	0	0	0			0	0	0		0
	0	0	0	0	0	A			0	0
	A	-A	0	0	0	0			A	-A
	0	0	0	0	0	0			0	0
aeV[V ²]	0	A	0			A	0	0		0
	A	0	0			0	-A	0		0
	0	0	0			0	0	0		0
	0	-A	0			-A	0	0		0
	-A	0	0			0	A	0		0
	0	0	0			0	0	0		0
	0	0	0	0	0	A			0	0
	A	-A	0	0	0	0			-A	A
	0	0	0	0	0	0			0	0

$[V^3]$

$$\begin{array}{ccc|ccc|ccc} 0 & A & 0 & A & 0 & 0 & 0 & 0 & 0 \\ A & 0 & 0 & 0 & -A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc|ccc|ccc} 0 & A & 0 & A & 0 & 0 & 0 & 0 & 0 \\ A & 0 & 0 & 0 & -A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc|ccc|ccc} 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ A & -A & 0 & A & -A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$ae[V^3]$

$$\begin{array}{ccc|ccc|ccc} 0 & A & 0 & A & 0 & 0 & 0 & 0 & 0 \\ A & 0 & 0 & 0 & -A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc|ccc|ccc} 0 & -A & 0 & -A & 0 & 0 & 0 & 0 & 0 \\ -A & 0 & 0 & 0 & A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$$\begin{array}{ccc|ccc|ccc} 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ A & -A & 0 & -A & A & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

$$26.9(4) \quad \overline{6}_{z m_x 2_1 1'} [\overline{6}_{z' m_x 2_1'}]$$

	$\overline{6}_z, m_x 2_1, \underline{1}'$					$\overline{6}_z, m_x 2_1 (3_z, m_x) \underline{1}'$				
V	0					0				
	0					0				
	0					0				
aeV	0					0				
	0					0				
	0					0				
[V ²]	A	0	0			A	0	0		
	0	A	0			0	A	0		
	0	0	B			0	0	B		
aeV ²	0	A	0			0	-A	0		
	-A	0	0			A	0	0		
	0	0	0			0	0	0		
V[V ²]	0	A	0			A	0	0		0 0 0
	A	0	0			0	-A	0		0 0 0
	0	0	0			0	0	0		0 0 0
	0	A	0			A	0	0		0 0 0
	A	0	0			0	-A	0		0 0 0
	0	0	0			0	0	0		0 0 0
	0	0	0	0	0	A			0	0 0 0 0 0 A
	A	-A	0	0	0	0			A	-A 0 0 0 0 0
	0	0	0	0	0	0			0	0 0 0 0 0 0
aeV[V ²]	-A	0	0			0	A	0		0 0 0
	0	A	0			A	0	0		0 0 0
	0	0	0			0	0	0		0 0 0
	A	0	0			0	-A	0		0 0 0
	0	-A	0			-A	0	0		0 0 0
	0	0	0			0	0	0		0 0 0
	-A	A	0	0	0	0			A	-A 0 0 0 0 0
	0	0	0	0	0	A			0	0 0 0 0 0 -A
	0	0	0	0	0	0			0	0 0 0 0 0 0

$[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0

0	0	0	0		0	0	0	0
A	-A	0			A	-A	0	
0	0	0			0	0	0	

$ae[V^3]$

-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0

-A	A	0	0		A	-A	0	0
0	0	0			0	0	0	
0	0	0			0	0	0	

26.11(5) $\overline{6}_z 'm_x 2_1' [3_z m_x]$

	$\overline{6}_z \text{ 'm}_x 2_1 \text{ '}$	$\overline{6}_z \text{m}_x 2_1 (3_z \text{m}_x) \{ 3_z \text{m}_x \}$		
V	0	0		
	0	0		
	A	-A		
aeV	0	0		
	0	0		
	0	0		
[V ²]	A 0 0	A 0 0		
	0 A 0	0 A 0		
	0 0 B	0 0 B		
aeV ²	0 A 0	0 A 0		
	-A 0 0	-A 0 0		
	0 0 0	0 0 0		
V[V ²]	0 A B	A 0 0	C 0 0	
	A 0 0	0 -A B	0 C 0	
	B 0 0	0 B 0	0 0 D	
	0 A -B	A 0 0	-C 0 0	
	A 0 0	0 -A -B	0 -C 0	
	-B 0 0	0 -B 0	0 0 -D	
	0 0 0 0 B A	0 0 0 0 -B A		
	A -A 0 B 0 0	A -A 0 -B 0 0		
	C C D 0 0 0	-C -C -D 0 0 0		
	aeV[V ²]	A 0 0	0 -A -B	0 0 0
		0 -A B	-A 0 0	0 0 0
		0 B 0	-B 0 0	0 0 0
A 0 0		0 -A B	0 0 0	
0 -A -B		-A 0 0	0 0 0	
0 -B 0		B 0 0	0 0 0	
A -A 0 B 0 0		A -A 0 -B 0 0		
0 0 0 0 -B -A		0 0 0 0 B -A		
0 0 0 0 0 0		0 0 0 0 0 0		

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	-B		A	0	0		-B	0	0
A	0	0		0	-A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		-B	-B	-C				

ae[V³]

A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	A	-A	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

26.12(6) $\overline{6}_z 'm_x 2_1' [3_z 2_1']$

	$\overline{6}_z 'm_x 2_1'$			$\overline{6}_z m_x 2_1 (3_z m_x) \{3_z 2_1 (3_z)\}$					
V	0			0					
	0			0					
	0			0					
aeV	0			0					
	0			0					
	A			-A					
[V ²]	A	0	0	A	0	0			
	0	A	0	0	A	0			
	0	0	B	0	0	B			
aeV ²	0	A	0	0	A	0			
	-A	0	0	-A	0	0			
	0	0	0	0	0	0			
V[V ²]	0	A	0	A	0	-B	0	0	0
	A	0	B	0	-A	0	0	0	0
	0	B	0	-B	0	0	0	0	0
	0	A	0	A	0	B	0	0	0
	A	0	-B	0	-A	0	0	0	0
	0	-B	0	B	0	0	0	0	0
	0	0	0	B	0	A	0	0	0
	A	-A	0	0	-B	0	A	-A	0
	0	0	0	0	0	0	0	0	0
aeV[V ²]	-A	0	B	0	A	0	C	0	0
	0	A	0	A	0	B	0	C	0
	B	0	0	0	B	0	0	0	D
	-A	0	-B	0	A	0	-C	0	0
	0	A	0	A	0	-B	0	-C	0
	-B	0	0	0	-B	0	0	0	-D
	-A	A	0	0	B	0	-A	A	0
	0	0	0	B	0	A	0	0	-B
	C	C	D	0	0	0	-C	-C	-D

[V³]

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	-A	0			A	-A	0			
0	0	0			0	0	0			

ae[V³]

-A	0	B		0	A	0		B	0	0
0	A	0		A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
-A	0	-B		0	A	0		-B	0	0
0	A	0		A	0	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
-A	A	0	0		-A	A	0	0		
0	0	0			0	0	0			
B	B	C			-B	-B	-C			

[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	B	0		B	A	0		0	0	0
B	A	0		A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
0	0	0		0	0	0				

ae[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-B	0		-B	-A	0		0	0	0
-B	-A	0		-A	B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	A	-A	0	0			
B	-B	0		-B	B	0				
0	0	0		0	0	0				

$$26.14(5) \quad \overline{6}_z ' m_x ' 2_1 [3_z 2_1]$$
$$\underline{\underline{6}}_z \text{ ' } \underline{m}_x \text{ ' } 2_1$$
$$\overline{6}_z m_x 2_1 (3_z 2_1) \{3_z 2_1\}$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
V[V ²]	0	A	0				A	0	-B				0	0	0
	A	0	B				0	-A	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	0	A	0				A	0	B				0	0	0
	A	0	-B				0	-A	0				0	0	0
	0	-B	0				B	0	0				0	0	0
	0	0	0	B	0	A				0	0	0	-B	0	A
	A	-A	0	0	-B	0				A	-A	0	0	B	0
	0	0	0	0	0	0				0	0	0	0	0	0
aeV[V ²]	0	A	0				A	0	-B				0	0	0
	A	0	B				0	-A	0				0	0	0
	0	B	0				-B	0	0				0	0	0
	0	A	0				A	0	B				0	0	0
	A	0	-B				0	-A	0				0	0	0
	0	-B	0				B	0	0				0	0	0
	0	0	0	B	0	A				0	0	0	-B	0	A
	A	-A	0	0	-B	0				A	-A	0	0	B	0
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	-A	0			A	-A	0			
0	0	0			0	0	0			

ae[V³]

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	-A	0			A	-A	0			
0	0	0			0	0	0			

$$26.15(6) \quad \overline{6}_z 'm_x' 2_1 [3_z m_x']$$

	$\overline{6}_z, m_x, 2_1$	$\overline{6}_z, m_x, 2_1 (3_z, 2_1) \{3_z, m_x (3_z)\}$
V	0 0 A	0 0 -A
aeV	0 0 A	0 0 -A
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
V[V ²]	0 A B A 0 0 B 0 0 0 A -B A 0 0 -B 0 0 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0	A 0 0 0 -A B 0 B 0 A 0 0 0 -A -B 0 -B 0 0 0 0 0 -B A A -A 0 -B 0 0 -C -C -D 0 0 0
aeV[V ²]	0 A B A 0 0 B 0 0 0 A -B A 0 0 -B 0 0 0 0 0 0 B A A -A 0 B 0 0 C C D 0 0 0	A 0 0 0 -A B 0 B 0 A 0 0 0 -A -B 0 -B 0 0 0 0 0 -B A A -A 0 -B 0 0 -C -C -D 0 0 0

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	-B		A	0	0		-B	0	0
A	0	0		0	-A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		-B	-B	-C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	-B		A	0	0		-B	0	0
A	0	0		0	-A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		-B	-B	-C				

$$26.16(6) \quad \overline{6}_z 'm_x' 2_1 [\overline{6}_z ']$$

$$\overline{6}_z 'm_x' 2_1$$

$$\overline{6}_z m_x 2_1 (3_z 2_1) \{ \overline{6}_z (3_z) \}$$

V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	0						0								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	A	C	0				A	-C	0						
	-C	A	0				C	A	0						
	0	0	B				0	0	B						
V[V ²]	A	B	0				B	-A	0				0	0	0
	B	-A	0				-A	-B	0				0	0	0
	0	0	0				0	0	0				0	0	0
	-A	B	0				B	A	0				0	0	0
	B	A	0				A	-B	0				0	0	0
	0	0	0				0	0	0				0	0	0
	A	-A	0	0	0	B				-A	A	0	0	0	B
	B	-B	0	0	0	-A				B	-B	0	0	0	A
	0	0	0	0	0	0				0	0	0	0	0	0
	A	B	0				B	-A	0				0	0	0
	B	-A	0				-A	-B	0				0	0	0
	0	0	0				0	0	0				0	0	0
aeV[V ²]	-A	B	0				B	A	0				0	0	0
	B	A	0				A	-B	0				0	0	0
	0	0	0				0	0	0				0	0	0
	A	-A	0	0	0	B				-A	A	0	0	0	B
	B	-B	0	0	0	-A				B	-B	0	0	0	A
	0	0	0	0	0	0				0	0	0	0	0	0

[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	B	0		B	A	0		0	0	0
B	A	0		A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
0	0	0		0	0	0				

ae[V³]

A	B	0		B	-A	0		0	0	0
B	-A	0		-A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	B	0		B	A	0		0	0	0
B	A	0		A	-B	0		0	0	0
0	0	0		0	0	0		0	0	0
A	-A	0	0	-A	A	0	0			
B	-B	0		B	-B	0				
0	0	0		0	0	0				

$$26.18(6) \quad \overline{6}_z m_x' 2_1' [3_z m_x']$$

	$\overline{6}_z m_x' 2_1'$			$\overline{6}_z m_x 2_1 (\overline{6}_z) \{3_z m_x (3_x)\}$		
V	0			0		
	0			0		
	A			-A		
aeV	0			0		
	0			0		
	A			A		
[V ²]	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	B	0	0	B
aeV ²	A	0	0	-A	0	0
	0	A	0	0	-A	0
	0	0	B	0	0	-B
V[V ²]	0	A	B	A	0	0
	A	0	0	0	-A	B
	B	0	0	0	B	0
	0	A	-B	A	0	0
	A	0	0	0	-A	-B
	-B	0	0	0	-B	0
	0	0	0	0	0	0
	A	-A	0	A	-A	0
	C	C	D	-C	-C	-D
aeV[V ²]	0	A	B	A	0	0
	A	0	0	0	-A	B
	B	0	0	0	B	0
	0	-A	B	-A	0	0
	-A	0	0	0	A	B
	B	0	0	0	B	0
	0	0	0	0	0	0
	A	-A	0	-A	A	0
	C	C	D	C	C	D

[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	A	-B		A	0	0		-B	0	0
A	0	0		0	-A	-B		0	-B	0
-B	0	0		0	-B	0		0	0	-C
0	0	0	0	0	0	0	0			
A	-A	0		A	-A	0				
B	B	C		-B	-B	-C				

ae[V³]

0	A	B		A	0	0		B	0	0
A	0	0		0	-A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	-A	B		-A	0	0		B	0	0
-A	0	0		0	A	B		0	B	0
B	0	0		0	B	0		0	0	C
0	0	0	0	0	0	0	0			
A	-A	0		-A	A	0				
B	B	C		B	B	C				

$$26.19(6) \quad \overline{6}_z m_x '2_1 '[3_z 2_1 ']$$

	$\overline{6}_z m_x '2_1 '$			$\overline{6}_z m_x 2_1 (\overline{6}_z) \{3_z 2_1 (3_z)\}$		
V	0			0		
	0			0		
	0			0		
aeV	0			0		
	0			0		
	A			A		
[V ²]	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	B	0	0	B
aeV ²	0	A	0	0	-A	0
	-A	0	0	A	0	0
	0	0	0	0	0	0
V[V ²]	0	A	0	A	0	-B
	A	0	B	0	-A	0
	0	B	0	-B	0	0
	0	A	0	A	0	B
	A	0	-B	0	-A	0
	0	-B	0	B	0	0
	0	0	0	B	0	0
	A	-A	0	0	-A	0
	0	0	0	0	0	0
aeV[V ²]	-A	0	B	0	A	0
	0	A	0	A	0	B
	B	0	0	0	B	0
	A	0	B	0	-A	0
	0	-A	0	-A	0	B
	B	0	0	0	B	0
	-A	A	0	A	-A	0
	0	0	0	0	0	0
	C	C	D	C	C	D

[V³]

0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	A	0		A	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	-A	0			A	-A	0			
0	0	0			0	0	0			

ae[V³]

-A	0	B		0	A	0		B	0	0
0	A	0		A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
A	0	B		0	-A	0		B	0	0
0	-A	0		-A	0	B		0	B	0
B	0	0		0	B	0		0	0	C
-A	A	0	0		A	-A	0	0		
0	0	0			0	0	0			
B	B	C			B	B	C			

27.3(1)

$6_z/m_z m_x m_1 [6_z 2_x 2_1]$

$6_z/m_z m_x m_1$

$6_z/m_z m_x m_1 \{6_z 2_x 2_1\}$

v	0						0									
	0						0									
	0						0									
aeV	0						0									
	0						0									
	0						0									
[v ²]	A	0	0				A	0	0							
	0	A	0				0	A	0							
	0	0	B				0	0	B							
aeV ²	A	0	0				-A	0	0							
	0	A	0				0	-A	0							
	0	0	B				0	0	-B							
v[v ²]	0	0	0				0	0	-A				0	0	0	
	0	0	A				0	0	0				0	0	0	
	0	A	0				-A	0	0				0	0	0	
	0	0	0				0	0	A				0	0	0	
	0	0	-A				0	0	0				0	0	0	
	0	-A	0				A	0	0				0	0	0	
	0	0	0	A	0	0				0	0	0	-A	0	0	
	0	0	0	0	-A	0				0	0	0	0	A	0	
	0	0	0	0	0	0				0	0	0	0	0	0	
	aeV[v ²]	0	0	0				0	0	-A				0	0	0
		0	0	A				0	0	0				0	0	0
		0	A	0				-A	0	0				0	0	0
0		0	0				0	0	-A				0	0	0	
0		0	A				0	0	0				0	0	0	
0		A	0				-A	0	0				0	0	0	
0		0	0	A	0	0				0	0	0	A	0	0	
0		0	0	0	-A	0				0	0	0	0	-A	0	
0		0	0	0	0	0				0	0	0	0	0	0	
aeV[v ²]		0	0	0				0	0	-A				0	0	0
		0	0	A				0	0	0				0	0	0
		0	A	0				-A	0	0				0	0	0
	0	0	0				0	0	-A				0	0	0	
	0	0	A				0	0	0				0	0	0	
	0	A	0				-A	0	0				0	0	0	
	0	0	0	A	0	0				0	0	0	A	0	0	
	0	0	0	0	-A	0				0	0	0	0	-A	0	
	0	0	0	0	0	0				0	0	0	0	0	0	

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

27.4(1)

$6_z/m_z m_x m_1 [6_z m_x m_1]$

$6_z/m_z m_x m_1$

$6_z/m_z m_x m_1 \{6_z m_x m_1\}$

V	0						0					
	0						0					
	A						-A					
aeV	0						0					
	0						0					
	0						0					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	0	A	0				0	-A	0			
	-A	0	0				A	0	0			
	0	0	0				0	0	0			
V[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	A	0	0	0	0	0	-A	0	0
	B	B	C	0	0	0	-B	-B	-C	0	0	0
	0	0	0				0	0	-A			
	0	0	A				0	0	0			
	0	A	0				-A	0	0			
aeV[V ²]	0	0	0				0	0	-A			
	0	0	A				0	0	0			
	0	A	0				-A	0	0			
	0	0	0				0	0	-A			
	0	0	A				0	0	0			
	0	A	0				-A	0	0			
	0	0	0	A	0	0	0	0	0	A	0	0
	0	0	0	0	-A	0	0	0	0	0	-A	0
	0	0	0	0	0	0	0	0	0	0	0	0
	0	0	0				0	0	-A			
	0	0	A				0	0	0			
	0	A	0				-A	0	0			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

	$\delta_z/m_z, m_x, m_1, \underline{1}$	$\delta_z/m_z m_x m_1 (\delta_z 2_x 2_1) \underline{1}$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 A 0 0 0 B	-A 0 0 0 -A 0 0 0 -B
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$27.22(6) \quad 6_z' / m_z' m_{x1}' [\overline{6}_z' m_{x21}']$$

$$\underline{6}_z \rightarrow m_z \rightarrow m_x m_1$$

$$6_z/m_z m_x m_1(\overline{3}_z m_x) \{ \overline{6}_z m_x 2_1(3_z m_x) \}$$

V	0						0							
	0						0							
	0						0							
aeV	0						0							
	0						0							
	0						0							
[V ²]	A	0	0				A	0	0					
	0	A	0				0	A	0					
	0	0	B				0	0	B					
aeV ²	0	A	0				0	-A	0					
	-A	0	0				A	0	0					
	0	0	0				0	0	0					
V[V ²]	0	A	0				A	0	0	0	0	0		
	A	0	0				0	-A	0	0	0	0		
	0	0	0				0	0	0	0	0	0		
	0	-A	0				-A	0	0	0	0	0		
	-A	0	0				0	A	0	0	0	0		
	0	0	0				0	0	0	0	0	0		
	0	0	0	0	0	A				0	0	0	0	-A
	A	-A	0	0	0	0				-A	A	0	0	0
	0	0	0	0	0	0				0	0	0	0	0
aeV[V ²]	-A	0	0				0	A	0	0	0	0		
	0	A	0				A	0	0	0	0	0		
	0	0	0				0	0	0	0	0	0		
	-A	0	0				0	A	0	0	0	0		
	0	A	0				A	0	0	0	0	0		
	0	0	0				0	0	0	0	0	0		
	-A	A	0	0	0	0				-A	A	0	0	0
	0	0	0	0	0	A				0	0	0	0	A
	0	0	0	0	0	0				0	0	0	0	0

$[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	0	0		0	0	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	$-A$	0			$-A$	A	0			
0	0	0			0	0	0			

$ae[V^3]$

$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	A	0	0		$-A$	A	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	-A	0		0	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	A	0	0		A	-A	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
-A	A	0	0		-A	A	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

27.26(6) $6_z/m_z m_x 'm_1' [6_z 2_x '2_1']$

	$6_z/\underline{m_z m_x} \, ' \underline{m_1} \, '$			$6_z/m_z m_x m_1 \, (\, 6_z/m_z \,) \, \{ \, 6_z 2_x 2_1 \, (\, 6_z \,) \, \}$											
V	0						0								
	0						0								
	0						0								
aeV	0						0								
	0						0								
	A						A								
[V ²]	A	0	0				A	0	0						
	0	A	0				0	A	0						
	0	0	B				0	0	B						
aeV ²	0	A	0				0	-A	0						
	-A	0	0				A	0	0						
	0	0	0				0	0	0						
V[V ²]	0	0	0				0	0	-A		0	0	0		
	0	0	A				0	0	0		0	0	0		
	0	A	0				-A	0	0		0	0	0		
	0	0	0				0	0	A		0	0	0		
	0	0	-A				0	0	0		0	0	0		
	0	-A	0				A	0	0		0	0	0		
	0	0	0	A	0	0				0	0	0	-A	0	0
	0	0	0	0	-A	0				0	0	0	0	A	0
	0	0	0	0	0	0				0	0	0	0	0	0
	0	0	A				0	0	0		B	0	0		
	0	0	0				0	0	A		0	B	0		
	A	0	0				0	A	0		0	0	C		
aeV[V ²]	0	0	A				0	0	0		B	0	0		
	0	0	0				0	0	A		0	B	0		
	A	0	0				0	A	0		0	0	C		
	0	0	A				0	0	0		B	0	0		
	0	0	0				0	0	A		0	B	0		
	A	0	0				0	A	0		0	0	C		
	0	0	0	0	A	0				0	0	0	0	A	0
	0	0	0	A	0	0				0	0	0	A	0	0
	B	B	C	0	0	0				B	B	C	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			A	A	B			

27.27(6) $6_z/m_z m_x 'm_1' [6_z m_x 'm_1']$

	$6_z/m_z m_x 'm_1'$			$6_z/m_z m_x m_1 (6_z/m_z) \{6_z m_x m_1 (6_z)\}$		
V	0			0		
	0			0		
	A			-A		
aeV	0			0		
	0			0		
	A			A		
[V ²]	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	B	0	0	B
aeV ²	A	0	0	-A	0	0
	0	A	0	0	-A	0
	0	0	B	0	0	-B
V[V ²]	0	0	A	0	0	0
	0	0	0	0	0	A
	A	0	0	0	A	0
	0	0	-A	0	0	0
	0	0	0	0	0	-A
	-A	0	0	0	-A	0
	0	0	0	0	0	0
	0	0	0	0	0	A
	0	0	0	0	0	-A
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
aeV[V ²]	0	0	A	0	0	0
	0	0	0	0	0	A
	A	0	0	0	A	0
	0	0	A	0	0	0
	0	0	0	0	0	A
	A	0	0	0	A	0
	0	0	0	0	0	0
	0	0	0	0	0	A
	0	0	0	0	0	-A
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		A	A	B				

27.29(5) $6_z/m_z'm_x'm_1'[6_z2_x2_1]$

	$6_z/m_z'm_x'm_1'$			$6_z/m_zm_xm_1(6_z2_x2_1)\{6_z2_x2_1\}$								
V	0			0								
	0			0								
	0			0								
aeV	0			0								
	0			0								
	0			0								
[V ²]	A	0	0	A 0 0								
	0	A	0	0 A 0								
	0	0	B	0 0 B								
aeV ²	A	0	0	A 0 0								
	0	A	0	0 A 0								
	0	0	B	0 0 B								
V[V ²]	0	0	0	0	0	-A	0	0	0	0	0	0
	0	0	A	0	0	0	0	0	0	0	0	0
	0	A	0	-A	0	0	0	0	0	0	0	0
	0	0	0	0	0	A	0	0	0	0	0	0
	0	0	-A	0	0	0	0	0	0	0	0	0
	0	-A	0	A	0	0	0	0	0	0	0	0
	0	0	0	A	0	0	0	0	0	0	-A	0 0
	0	0	0	0	-A	0	0	0	0	0	0	A 0
	0	0	0	0	0	0	0	0	0	0	0	0 0
	0	0	0	0	0	-A	0	0	0	0	0	0
	0	0	A	0	0	0	0	0	0	0	0	0
	0	A	0	-A	0	0	0	0	0	0	0	0
aeV[V ²]	0	0	0	0	0	-A	0	0	0	0	0	0
	0	0	A	0	0	0	0	0	0	0	0	0
	0	A	0	-A	0	0	0	0	0	0	0	0
	0	0	0	0	0	A	0	0	0	0	0	0
	0	0	-A	0	0	0	0	0	0	0	0	0
	0	-A	0	A	0	0	0	0	0	0	0	0
	0	0	0	A	0	0	0	0	0	0	-A	0 0
	0	0	0	0	-A	0	0	0	0	0	0	A 0
	0	0	0	0	0	0	0	0	0	0	0	0 0
	0	0	0	0	0	-A	0	0	0	0	0	0
	0	0	A	0	0	0	0	0	0	0	0	0
	0	A	0	-A	0	0	0	0	0	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$$27.30(6) \quad 6_z/m_z'm_x'm_1'[\overline{3}_z'm_x']$$

$$\underline{6}_z / \underline{m}_z \text{ ' } \underline{m}_x \text{ ' } \underline{m}_1 \text{ '}$$

$$6_z/m_z m_x m_1(6_z 2_x 2_1)\{\overline{3}_z m_x(3_z 2_x)\}$$

V	0 0 0		0 0 0
aeV	0 0 0		0 0 0
[V ²]	A 0 0 0 A 0 0 0 B		A 0 0 0 A 0 0 0 B
aeV ²	A 0 0 0 A 0 0 0 B		A 0 0 0 A 0 0 0 B
V[V ²]	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$27.31(6) \quad 6_z/m_z 'm_x 'm_1 '[6_z/m_z ']$$

	$6_z/m_z \, ' \underline{m_x} \, ' \underline{m_1} \, '$						$6_z/m_z m_x m_1 (\, 6_z 2_x 2_1 \,) \, \{ \, 6_z/m_z (\, 6_z \,) \, \}$									
V	0						0									
	0						0									
	0						0									
aeV	0						0									
	0						0									
	0						0									
[V ²]	A 0 0						A 0 0									
	0 A 0						0 A 0									
	0 0 B						0 0 B									
aeV ²	A C 0						A -C 0									
	-C A 0						C A 0									
	0 0 B						0 0 B									
V[V ²]	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					
aeV[V ²]	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0						0 0 0				0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					
	0 0 0 0 0 0						0 0 0 0 0 0				0 0 0 0 0 0					

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$6_z/m_z'm_x'm_1'[6_zm_x'm_1']$$
$$6_z/m_z m_x m_1 (6_z 2_x 2_1) \{6_z m_x m_1 (6_z)\}$$

V	0						0					
	0						0					
	A						-A					
aeV	0						0					
	0						0					
	A						-A					
[V ²]	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
aeV ²	A	0	0				A	0	0			
	0	A	0				0	A	0			
	0	0	B				0	0	B			
V[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	A	0	0	0	0	0	-A	0	0
	B	B	C	0	0	0	-B	-B	-C	0	0	0
aeV[V ²]	0	0	A				0	0	0	B	0	0
	0	0	0				0	0	A	0	B	0
	A	0	0				0	A	0	0	0	C
	0	0	-A				0	0	0	-B	0	0
	0	0	0				0	0	-A	0	-B	0
	-A	0	0				0	-A	0	0	0	-C
	0	0	0	0	A	0	0	0	0	0	-A	0
	0	0	0	A	0	0	0	0	0	-A	0	0
	B	B	C	0	0	0	-B	-B	-C	0	0	0

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	-A		-A	0	0
0	0	0		0	0	0		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

$$27.33(6) \quad 6_z/m_z'm_x'm_1'[\overline{6}_z'm_x'2_1']$$

	$\overline{6}_z/m_z \text{ 'm}_x \text{ 'm}_1 \text{ '}$	$6_z/m_z m_x m_1 (6_z 2_x 2_1) \{ \overline{6}_z m_x 2_1 (3_z 2_1) \}$	
V	0 0 0	0 0 0	
aeV	0 0 0	0 0 0	
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B	
aeV ²	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B	
V[V ²]	0 A 0 A 0 0 0 0 0	A 0 0 0 -A 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 -A 0 -A 0 0 0 0 0	-A 0 0 0 A 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 A A -A 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 -A -A A 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 A 0 A 0 0 0 0 0	A 0 0 0 -A 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 -A 0 -A 0 0 0 0 0	-A 0 0 0 A 0 0 0 0	0 0 0 0 0 0 0 0 0
	0 0 0 0 0 A A -A 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 -A -A A 0 0 0 0 0 0 0 0 0 0

$[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	0	0		0	0	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	$-A$	0			$-A$	A	0			
0	0	0			0	0	0			

$ae[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	0	0		0	0	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	$-A$	0			$-A$	A	0			
0	0	0			0	0	0			

[V³]

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
A	A	B		-A	-A	-B				

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0	0	0	0	0			
0	0	0		0	0	0				
0	0	0		0	0	0				

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

27.37(6) $6_z/m_z' m_x m_1 [6_z 2_x' 2_1']$

	$6_z/m_z' m_x m_1$			$6_z/m_z m_x m_1 (6_z m_x m_1) \{6_z 2_x 2_1 (6_z)\}$								
V	0											
	0											
	0											
aeV	0											
	0											
	A											
[V ²]	A	0	0									
	0	A	0									
	0	0	B									
aeV ²	0	A	0									
	-A	0	0									
	0	0	0									
V[V ²]	0	0	0									
	0	0	A									
	0	A	0									
	0	0	0									
	0	0	-A									
	0	-A	0									
	0	0	0	A	0	0						
	0	0	0	0	-A	0						
	0	0	0	0	0	0						
aeV[V ²]	0	0	A									
	0	0	0									
	A	0	0									
	0	0	-A									
	0	0	0									
	-A	0	0									
	0	0	0	0	A	0						
	0	0	0	A	0	0						
	B	B	C	0	0	0						

$[V^3]$

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

$ae[V^3]$

0	0	A		0	0	0		A	0	0
0	0	0		0	0	A		0	A	0
A	0	0		0	A	0		0	0	B
0	0	-A		0	0	0		-A	0	0
0	0	0		0	0	-A		0	-A	0
-A	0	0		0	-A	0		0	0	-B
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
A	A	B			-A	-A	-B			

$$27.38(6) \quad 6_z/m_z 'm_x m_1 [\overline{6}_z 'm_x 2_1 ']$$

	$\underline{6_z}/m_z \cdot m_{x1}$	$6_z/m_z m_x m_1 (6_z m_x m_1) \{ \overline{6_z} m_x 2_1 (3_z m_x) \}$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
[V ²]	A 0 0 0 A 0 0 0 B	A 0 0 0 A 0 0 0 B
aeV ²	0 A 0 -A 0 0 0 0 0	0 A 0 -A 0 0 0 0 0
V[V ²]	0 A 0 A 0 0 0 0 0	A 0 0 0 -A 0 0 0 0
	0 -A 0 -A 0 0 0 0 0	-A 0 0 0 A 0 0 0 0
	0 0 0 0 0 A A -A 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 -A -A A 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	-A 0 0 0 A 0 0 0 0	0 A 0 A 0 0 0 0 0
	A 0 0 0 -A 0 0 0 0	0 -A 0 -A 0 0 0 0 0
	-A A 0 0 0 0 0 0 0 0 0 A 0 0 0 0 0 0	A -A 0 0 0 0 0 0 0 0 0 -A 0 0 0 0 0 0

$[V^3]$

0	A	0		A	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	0	0		0	0	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
$-A$	0	0		0	A	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
A	$-A$	0			$-A$	A	0			
0	0	0			0	0	0			

$ae[V^3]$

$-A$	0	0		0	A	0		0	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	0		0	0	0
A	0	0		0	$-A$	0		0	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0		0	0	0		0	0	0
$-A$	A	0	0		A	$-A$	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0		0	
0	0	0			0	0	0		0	

	$\underline{6}_z / \underline{m}_z \underline{m}_x \underline{m}_1$	$\underline{6}_z / \underline{m}_z \underline{m}_x \underline{m}_1 (\overline{6}_z \underline{m}_x 2_1) \{ \overline{3}_z \underline{m}_1 (3_z 2_1) \}$																
V	0							0										
	0							0										
	0							0										
aeV	0							0										
	0							0										
	0							0										
[V ²]	A	0	0				A	0	0									
	0	A	0				0	A	0									
	0	0	B				0	0	B									
aeV ²	A	0	0				-A	0	0									
	0	A	0				0	-A	0									
	0	0	B				0	0	-B									
V[V ²]	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
aeV[V ²]	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0				0	0	0				0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			
	0	0	0	0	0	0				0	0	0	0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

$$2_z 3_{xyz} 1' [2_z 3_{xyz}]$$

$$2_z 3_{xyz} \underline{1}'$$

V	0 0 0						0 0 0						
aeV	0 0 0						0 0 0						
[V ²]	A 0 0 0 A 0 0 0 A						A 0 0 0 A 0 0 0 A						
aeV ²	A 0 0 0 A 0 0 0 A						-A 0 0 0 -A 0 0 0 -A						
V[V ²]	0 0 0 0 0 A 0 A 0						0 0 A 0 0 0 A 0 0						
	0 0 0 0 0 A 0 A 0						0 0 A 0 0 0 A 0 0						
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A						0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A						
aeV[V ²]	0 0 0 0 0 A 0 A 0						0 0 A 0 0 0 A 0 0						
	0 0 0 0 0 -A 0 -A 0						0 0 -A 0 0 0 -A 0 0						
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A						0 0 0 -A 0 0 0 0 0 0 -A 0 0 0 0 0 0 -A						

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$m_z \overline{3}_{xyz} 1' [m_z' \overline{3}_{xyz}']$$
$$m_z \overline{3}_{xyz} (2_z 3_{xyz}) \underline{1}'$$

V	0 0 0		0 0 0	
aeV	0 0 0		0 0 0	
[V ²]	A 0 0 0 A 0 0 0 A		A 0 0 0 A 0 0 0 A	
aeV ²	A 0 0 0 A 0 0 0 A		-A 0 0 0 -A 0 0 0 -A	
V[V ²]	0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0	
	0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0	
	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	
aeV[V ²]	0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0	
	0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0	
	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$4_z 3_{xyz} 2_{xy} 1' [4_z 3_{xyz} 2_{xy}]$$
$$4_z 3_{xyz} 2_{xy} \underline{1}'$$
[illegible]

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		0
0	0	0			0	0	0			0
0	0	0			0	0	0			0

$[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	$-A$		0	$-A$	0
0	0	$-A$		0	0	0		$-A$	0	0
0	$-A$	0		$-A$	0	0		0	0	0
0	0	0	A		0	0	0	$-A$		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

31.1(1)

$\overline{4}_z 3_{xyz} m_{xy} [2_z 3_{xyz}]$

$\underline{\underline{4}}_z 3_{xyz} m_{xy}$

$\overline{4}_z 3_{xyz} m_{xy} \{2_z 3_{xyz}\}$

V	0 0 0	0 0 0	
aeV	0 0 0	0 0 0	
[V ²]	A 0 0 0 A 0 0 0 A	A 0 0 0 A 0 0 0 A	
aeV ²	A 0 0 0 A 0 0 0 A	-A 0 0 0 -A 0 0 0 -A	
V[V ²]	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A		0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A
aeV[V ²]	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 0 0 -A 0 -A 0	0 0 -A 0 0 0 -A 0 0	0 -A 0 -A 0 0 0 0 0
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A		0 0 0 -A 0 0 0 0 0 0 -A 0 0 0 0 0 0 -A

$[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$ae[V^3]$

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

31.4(4)

$$\overline{4}_z 3_{xyz} m_{xy} 1' [\overline{4}_z' 3_{xyz} m_{xy}']$$

$$\overline{4}_z' 3_{xyz} m_{xy}' \underline{1}'$$

$$\overline{4}_z 3_{xyz} m_{xy} (2_z 3_{xyz}) \underline{1}'$$

V

$$\begin{matrix} 0 \\ 0 \\ 0 \end{matrix}$$

$$\begin{matrix} 0 \\ 0 \\ 0 \end{matrix}$$

aeV

$$\begin{matrix} 0 \\ 0 \\ 0 \end{matrix}$$

$$\begin{matrix} 0 \\ 0 \\ 0 \end{matrix}$$

[V²]

$$\begin{matrix} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{matrix}$$

$$\begin{matrix} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{matrix}$$

aeV²

$$\begin{matrix} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{matrix}$$

$$\begin{matrix} -A & 0 & 0 \\ 0 & -A & 0 \\ 0 & 0 & -A \end{matrix}$$

V[V²]

$$\begin{matrix} 0 & 0 & 0 \\ 0 & 0 & A \\ 0 & A & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & A \\ 0 & 0 & 0 \\ A & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & A & 0 \\ A & 0 & 0 \\ 0 & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 \\ 0 & 0 & A \\ 0 & A & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & A \\ 0 & 0 & 0 \\ A & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & A & 0 \\ A & 0 & 0 \\ 0 & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 & A & 0 & 0 \\ 0 & 0 & 0 & 0 & A & 0 \\ 0 & 0 & 0 & 0 & 0 & A \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 & A & 0 & 0 \\ 0 & 0 & 0 & 0 & A & 0 \\ 0 & 0 & 0 & 0 & 0 & A \end{matrix}$$

aeV[V²]

$$\begin{matrix} 0 & 0 & 0 \\ 0 & 0 & A \\ 0 & A & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & A \\ 0 & 0 & 0 \\ A & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & A & 0 \\ A & 0 & 0 \\ 0 & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 \\ 0 & 0 & -A \\ 0 & -A & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & -A \\ 0 & 0 & 0 \\ -A & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & -A & 0 \\ -A & 0 & 0 \\ 0 & 0 & 0 \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 & A & 0 & 0 \\ 0 & 0 & 0 & 0 & A & 0 \\ 0 & 0 & 0 & 0 & 0 & A \end{matrix}$$

$$\begin{matrix} 0 & 0 & 0 & -A & 0 & 0 \\ 0 & 0 & 0 & 0 & -A & 0 \\ 0 & 0 & 0 & 0 & 0 & -A \end{matrix}$$

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

31.5(5)

$$\overline{4_z} ' 3_{xyz} m_{xy} ' [2_z 3_{xyz}]$$

$$\underline{\underline{4_z}} ' 3_{xyz} \underline{m_{xy}} '$$

$$\overline{4_z} 3_{xyz} m_{xy} (2_z 3_{xyz}) \{ 2_z 3_{xyz} \}$$

V	0 0 0	0 0 0	
aeV	0 0 0	0 0 0	
[V ²]	A 0 0 0 A 0 0 0 A	A 0 0 0 A 0 0 0 A	
aeV ²	A 0 0 0 A 0 0 0 A	A 0 0 0 A 0 0 0 A	
V[V ²]	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A		0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A
aeV[V ²]	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 0 0 A 0 A 0	0 0 A 0 0 0 A 0 0	0 A 0 A 0 0 0 0 0
	0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A		0 0 0 A 0 0 0 0 0 0 A 0 0 0 0 0 0 A

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

$$32.3(1) \quad m_z \overline{3}_{xyz} m_{xy} [4_z 3_{xyz} 2_{xy}]$$

	$\underline{m_z \overline{3}_{xyz} m_{xy}}$			$m_z \overline{3}_{xyz} m_{xy} \{ 4_z 3_{xyz} 2_{xy} \}$		
<hr/>						
V	0			0		
	0			0		
	0			0		
aeV	0			0		
	0			0		
	0			0		
[V ²]	A	0	0	A	0	0
	0	A	0	0	A	0
	0	0	A	0	0	A
aeV ²	A	0	0	-A	0	0
	0	A	0	0	-A	0
	0	0	A	0	0	-A
V[V ²]	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
aeV[V ²]	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0
	0	0	0	0	0	0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

32.13(6)

$$m_z \bar{3}_{xyz} m_{xy}' [\bar{4}_z' 3_{xyz} m_{xy}']$$

$$\underline{m_z \bar{3}_{xyz} m_{xy}'}$$

$$m_z \bar{3}_{xyz} m_{xy} (m_z \bar{3}_{xyz}) \{ \bar{4}_z 3_{xyz} m_{xy} (2_z 3_{xyz}) \}$$

V	0	0	0
	0	0	0
	0	0	0
aeV	0	0	0
	0	0	0
	0	0	0
[V ²]	A 0 0	A 0 0	
	0 A 0	0 A 0	
	0 0 A	0 0 A	
aeV ²	A 0 0	-A 0 0	
	0 A 0	0 -A 0	
	0 0 A	0 0 -A	
V[V ²]	0 0 0	0 0 A	0 A 0
	0 0 A	0 0 0	A 0 0
	0 A 0	A 0 0	0 0 0
	0 0 0	0 0 -A	0 -A 0
	0 0 -A	0 0 0	-A 0 0
	0 -A 0	-A 0 0	0 0 0
	0 0 0 A 0 0	0 0 0 -A 0 0	0 0 0
	0 0 0 0 A 0	0 0 0 0 -A 0	0 0 0
	0 0 0 0 0 A	0 0 0 0 0 -A	0 0 0
aeV[V ²]	0 0 0	0 0 A	0 A 0
	0 0 A	0 0 0	A 0 0
	0 A 0	A 0 0	0 0 0
	0 0 0	0 0 A	0 A 0
	0 0 A	0 0 0	A 0 0
	0 A 0	A 0 0	0 0 0
	0 0 0 A 0 0	0 0 0 A 0 0	0 0 0
	0 0 0 0 A 0	0 0 0 0 A 0	0 0 0
	0 0 0 0 0 A	0 0 0 0 0 A	0 0 0

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0	A		0	0	0	A		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

	$m_z \, ' \overline{3}_{xyz} \, ' \underline{m}_{xy} \, '$	$m_z \, \overline{3}_{xyz} m_{xy} \, (\, 4_z \, \overline{3}_{xyz} \, 2_{xy} \,) \, \{ m_z \, \overline{3}_{xyz} \, (\, 2_z \, \overline{3}_{xyz} \,) \, \}$
V	0 0 0	0 0 0
aeV	0 0 0	0 0 0
$[V^2]$	A 0 0 0 A 0 0 0 A	A 0 0 0 A 0 0 0 A
aeV ²	A 0 0 0 A 0 0 0 A	A 0 0 0 A 0 0 0 A
V[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
aeV[V ²]	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	A		0	A	0
0	0	A		0	0	0		A	0	0
0	A	0		A	0	0		0	0	0
0	0	0		0	0	-A		0	-A	0
0	0	-A		0	0	0		-A	0	0
0	-A	0		-A	0	0		0	0	0
0	0	0	A		0	0	0	-A		
0	0	0			0	0	0			
0	0	0			0	0	0			

32.18(6)

$$m_z ' \overline{3}_{xyz} ' m_{xy} [m_z ' \overline{3}_{xyz} ']$$

$$m_z ' \overline{3}_{xyz} ' \underline{m}_{xy}$$

$$m_z \overline{3}_{xyz} m_{xy} (\overline{4}_z \overline{3}_{xyz} m_{xy}) \{ m_z \overline{3}_{xyz} (2_z \overline{3}_{xyz}) \}$$

V

$$\begin{array}{c} 0 \\ 0 \\ 0 \end{array} \qquad \begin{array}{c} 0 \\ 0 \\ 0 \end{array}$$

aeV

$$\begin{array}{c} 0 \\ 0 \\ 0 \end{array} \qquad \begin{array}{c} 0 \\ 0 \\ 0 \end{array}$$

[V²]

$$\begin{array}{ccc} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{array} \qquad \begin{array}{ccc} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{array}$$

aeV²

$$\begin{array}{ccc} A & 0 & 0 \\ 0 & A & 0 \\ 0 & 0 & A \end{array} \qquad \begin{array}{ccc} -A & 0 & 0 \\ 0 & -A & 0 \\ 0 & 0 & -A \end{array}$$

V[V²]

$$\begin{array}{ccc|ccc|ccc} 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

aeV[V²]

$$\begin{array}{ccc|ccc|ccc} 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{array}$$

[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

ae[V³]

0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0		0	0	0		0	0	0
0	0	0	0		0	0	0	0		
0	0	0			0	0	0			
0	0	0			0	0	0			

